




## INTERNATIONAL APPLICATION PUBLISHED UNDER THE PATENT COOPERATION TREATY (PCT)

(51) International Patent Classification <sup>6</sup> : <b>G01R 31/08, H04L 12/28, 12/66</b>		A1	(11) International Publication Number: <b>WO 00/03256</b>
			(43) International Publication Date: 20 January 2000 (20.01.00)
(21) International Application Number: PCT/US99/14821		(81) Designated States: AE, AL, AM, AT, AU, AZ, BA, BB, BG, BR, BY, CA, CH, CN, CU, CZ, DE, DK, EE, ES, FI, GB, GD, GE, GH, GM, HR, HU, ID, IL, IN, IS, JP, KE, KG, KP, KR, KZ, LC, LK, LR, LS, LT, LU, LV, MD, MG, MK, MN, MW, MX, NO, NZ, PL, PT, RO, RU, SD, SE, SG, SI, SK, SL, TJ, TM, TR, TT, UA, UG, UZ, VN, YU, ZA, ZW, ARIPO patent (GH, GM, KE, LS, MW, SD, SL, SZ, UG, ZW), Eurasian patent (AM, AZ, BY, KG, KZ, MD, RU, TJ, TM), European patent (AT, BE, CH, CY, DE, DK, ES, FI, FR, GB, GR, IE, IT, LU, MC, NL, PT, SE), OAPI patent (BF, BJ, CF, CG, CI, CM, GA, GN, GW, ML, MR, NE, SN, TD, TG).	
(22) International Filing Date: 30 June 1999 (30.06.99)			
(30) Priority Data: 60/092,220 8 July 1998 (08.07.98) US 60/095,972 10 August 1998 (10.08.98) US			
(71) Applicant: BROADCOM CORPORATION [US/US]; 16215 Alton Parkway, P.O. Box 57013, Irvine, CA 92619-7013 (US).			
(72) Inventors: KADAMBI, Shiri; 1690 Park Hills Avenue, Los Altos, CA 94024 (US). AMBE, Shekhar; 3220 Verdant Way, San Jose, CA 95117 (US).			
(74) Agents: GOLDHUSH, Douglas, H. et al.; Nikaido, Marmelstein, Murray & Oram LLP, Suite 330, Metropolitan Square, 655 Fifteenth Street N.W., G Street Lobby, Washington, DC 20005-5701 (US).			
		Published With international search report.	

(54) Title: NETWORK SWITCH UTILIZING PACKET BASED PER HEAD-OF-LINE BLOCKING PREVENTION



## (57) Abstract

A network switch for network communications includes a first data port interface (20) which supports a plurality of data ports which transmit and receive data at a first rate. A second data port interface (30) is provided and supports a plurality of data ports transmitting and receiving data at a second rate. A CPU interface (40) is provided, configured to communicate with a CPU. An internal memory (50) is provided, and communicates with the first data port interface and the second data port interface. A memory management unit is provided, and includes an external memory interface (70) for communicating data from at least one of the first data port interface and the second data port interface and an external memory. A communication channel (80) is provided, with the channel communicating data between the at least one first data port interface, the at least one second data port interface, the internal memory, and the memory management.

**FOR THE PURPOSES OF INFORMATION ONLY**

Codes used to identify States party to the PCT on the front pages of pamphlets publishing international applications under the PCT.

AL	Albania	ES	Spain	LS	Lesotho	SI	Slovenia
AM	Armenia	FI	Finland	LT	Lithuania	SK	Slovakia
AT	Austria	FR	France	LU	Luxembourg	SN	Senegal
AU	Australia	GA	Gabon	LV	Latvia	SZ	Swaziland
AZ	Azerbaijan	GB	United Kingdom	MC	Monaco	TD	Chad
BA	Bosnia and Herzegovina	GE	Georgia	MD	Republic of Moldova	TG	Togo
BB	Barbados	GH	Ghana	MG	Madagascar	TJ	Tajikistan
BE	Belgium	GN	Guinea	MK	The former Yugoslav Republic of Macedonia	TM	Turkmenistan
BF	Burkina Faso	GR	Greece			TR	Turkey
BG	Bulgaria	HU	Hungary	ML	Mali	TT	Trinidad and Tobago
BJ	Benin	IE	Ireland	MN	Mongolia	UA	Ukraine
BR	Brazil	IL	Israel	MR	Mauritania	UG	Uganda
BY	Belarus	IS	Iceland	MW	Malawi	US	United States of America
CA	Canada	IT	Italy	MX	Mexico	UZ	Uzbekistan
CF	Central African Republic	JP	Japan	NE	Niger	VN	Viet Nam
CG	Congo	KE	Kenya	NL	Netherlands	YU	Yugoslavia
CH	Switzerland	KG	Kyrgyzstan	NO	Norway	ZW	Zimbabwe
CI	Côte d'Ivoire	KP	Democratic People's Republic of Korea	NZ	New Zealand		
CM	Cameroon			PL	Poland		
CN	China	KR	Republic of Korea	PT	Portugal		
CU	Cuba	KZ	Kazakhstan	RO	Romania		
CZ	Czech Republic	LC	Saint Lucia	RU	Russian Federation		
DE	Germany	LI	Liechtenstein	SD	Sudan		
DK	Denmark	LK	Sri Lanka	SE	Sweden		
EE	Estonia	LR	Liberia	SG	Singapore		

**TITLE OF THE INVENTION:**

**NETWORK SWITCH UTILIZING PACKET BASED PER HEAD-OF-LINE BLOCKING PREVENTION**

**5      REFERENCE TO RELATED APPLICATIONS:**

This application claims priority of United States Provisional Patent Application Serial No. 60/092,220, filed on July 8, 1998, and U.S. Provisional Application No. 60/095,972, filed on August 10, 1998. The contents of these provisional applications is hereby incorporated by reference.

**10     BACKGROUND OF THE INVENTION:****Field of the Invention:**

The invention relates to a method and apparatus for high performance switching in local area communications networks such as token ring, ATM, ethernet, fast ethernet, and gigabit ethernet environments, generally known  
**15     as LANs. In particular, the invention relates to a new switching architecture in an integrated, modular, single chip solution, which can be implemented on a semiconductor substrate such as a silicon chip.**

**Description of the Related Art:**

As computer performance has increased in recent years, the demands  
**20     on computer networks has significantly increased; faster computer processors and higher memory capabilities need networks with high bandwidth capabilities to enable high speed transfer of significant amounts of data. The well-known ethernet technology, which is based upon numerous IEEE ethernet standards, is one example of computer networking technology which**  
**25     has been able to be modified and improved to remain a viable computing technology. A more complete discussion of prior art networking systems can be found, for example, in SWITCHED AND FAST ETHERNET, by Breyer and Riley (Ziff-Davis, 1996), and numerous IEEE publications relating to IEEE 802 standards. Based upon the Open Systems Interconnect (OSI) 7-layer**  
**30     reference model, network capabilities have grown through the development of repeaters, bridges, routers, and, more recently, "switches", which operate with various types of communication media. Thickwire, thinwire, twisted pair,**

and optical fiber are examples of media which has been used for computer networks. Switches, as they relate to computer networking and to ethernet, are hardware-based devices which control the flow of data packets or cells based upon destination address information which is available in each packet.

5 A properly designed and implemented switch should be capable of receiving a packet and switching the packet to an appropriate output port at what is referred to wirespeed or linespeed, which is the maximum speed capability of the particular network. Basic ethernet wirespeed is up to 10 megabits per second, and Fast Ethernet is up to 100 megabits per second. The newest

10 ethernet is referred to as gigabit ethernet, and is capable of transmitting data over a network at a rate of up to 1,000 megabits per second. As speed has increased, design constraints and design requirements have become more and more complex with respect to following appropriate design and protocol rules and providing a low cost, commercially viable solution. For example,

15 high speed switching requires high speed memory to provide appropriate buffering of packet data; conventional Dynamic Random Access Memory (DRAM) is relatively slow, and requires hardware-driven refresh. The speed of DRAMs, therefore, as buffer memory in network switching, results in valuable time being lost, and it becomes almost impossible to operate the

20 switch or the network at linespeed. Furthermore, external CPU involvement should be avoided, since CPU involvement also makes it almost impossible to operate the switch at linespeed. Additionally, as network switches have become more and more complicated with respect to requiring rules tables and memory control, a complex multi-chip solution is necessary which requires

25 logic circuitry, sometimes referred to as glue logic circuitry, to enable the various chips to communicate with each other. Additionally, cost/benefit tradeoffs are necessary with respect to expensive but fast SRAMs versus inexpensive but slow DRAMs. Additionally, DRAMs, by virtue of their dynamic nature, require refreshing of the memory contents in order to prevent losses

30 thereof. SRAMs do not suffer from the refresh requirement, and have reduced operational overhead which compared to DRAMs such as elimination of page misses, etc. Although DRAMs have adequate speed when accessing

locations on the same page, speed is reduced when other pages must be accessed.

Referring to the OSI 7-layer reference model discussed previously, and illustrated in Figure 7, the higher layers typically have more information. Various types of products are available for performing switching-related functions at various levels of the OSI model. Hubs or repeaters operate at layer one, and essentially copy and "broadcast" incoming data to a plurality of spokes of the hub. Layer two switching-related devices are typically referred to as multiport bridges, and are capable of bridging two separate networks. Bridges can build a table of forwarding rules based upon which MAC (media access controller) addresses exist on which ports of the bridge, and pass packets which are destined for an address which is located on an opposite side of the bridge. Bridges typically utilize what is known as the "spanning tree" algorithm to eliminate potential data loops; a data loop is a situation wherein a packet endlessly loops in a network looking for a particular address. The spanning tree algorithm defines a protocol for preventing data loops. Layer three switches, sometimes referred to as routers, can forward packets based upon the destination network address. Layer three switches are capable of learning addresses and maintaining tables thereof which correspond to port mappings. Processing speed for layer three switches can be improved by utilizing specialized high performance hardware, and off loading the host CPU so that instruction decisions do not delay packet forwarding.

#### **SUMMARY OF THE INVENTION:**

The present invention is directed to a switch-on-chip solution for a network switch, capable of use at least on ethernet, fast ethernet, and gigabit ethernet systems, wherein all of the switching hardware is disposed on a single microchip. The present invention is configured to maximize the ability of packet-forwarding at linespeed, and to also provide a modular configuration wherein a plurality of separate modules are configured on a common chip, and wherein individual design changes to particular modules do not affect the relationship of that particular module to other modules in the system.

The invention is therefore directed to a network switch for network communications, with the data switch including a first data port interface. The data port interface supports a plurality of data ports which transmit and receive data at a first data rate. A second data port interface is provided; the  
5 second data port interface supports a plurality of data ports transmitting and receiving data at a second data rate. A CPU interface is provided, with the CPU interface configured to communicate with a CPU. An internal memory is provided, and communicates with the first data port interface and the at least one second data port interface. A memory management unit is provided,  
10 and includes an external memory interface for communicating data from at least one of the first data port interface and the second data port interface and an external memory. A communication channel is provided, with the communication channel communicating data and messaging information between the at least one first data port interface, the at least one second data  
15 port interface, the internal memory, and the memory management unit. One data port interface of the first data port interface and the second data port interface includes a head-of-line blocking prevention mechanism. This mechanism includes a determination means for determining when head-of-line blocking is occurring based upon cell based and packet based thresholds.

20 The mechanism can also include a communication means for communicating an occurrence of head-of-line blocking by sending a message to an ingress port of the one data port interface. The communication means sends the message if one threshold of the cell-based threshold and packet-based threshold is exceeded. The mechanism also includes deactivating  
25 means for deactivating a congested port at which the head-of-line blocking occurs, with respect to packets or cells destined for the congested port. The packet based thresholds are provided on a per port per class of service basis.

An embodiment of the invention may also be such that the head-of-line blocking prevention mechanism includes an output queue for each data port  
30 of the plurality of data ports. The output queue includes a high threshold and a low threshold. The mechanism is configured to deactivate a corresponding port when the output queue hits the high threshold.

The invention also includes an embodiment wherein an active port register is provided for indicating activation and deactivation of the corresponding port.

**BRIEF DESCRIPTION OF THE DRAWINGS:**

5           The objects and features of the invention will be more readily understood with reference to the following description and the attached drawings, wherein:

Figure 1 is a general block diagram of elements of the present invention;

10           Figure 2 is a more detailed block diagram of a network switch according to the present invention;

Figure 3 illustrates the data flow on the CPS channel of a network switch according to the present invention;

15           Figure 4A illustrates demand priority round robin arbitration for access to the C-channel of the network switch;

Figure 4B illustrates access to the C-channel based upon the round robin arbitration illustrated in Figure 4A;

Figure 5 illustrates P-channel message types;

Figure 6 illustrates a message format for S channel message types;

20           Figure 7 is an illustration of the OSI 7 layer reference model;

Figure 8 illustrates an operational diagram of an EPIC module;

Figure 9 illustrates the slicing of a data packet on the ingress to an EPIC module;

Figure 10 is a detailed view of elements of the PMMU;

25           Figure 11 illustrates the CBM cell format;

Figure 12 illustrates an internal/external memory admission flow chart;

Figure 13 illustrates a block diagram of an egress manager 76 illustrated in Figure 10;

Figure 14 illustrates more details of an EPIC module;

30           Figure 15 is a block diagram of a fast filtering processor (FFP);

Figure 16 is a block diagram of the elements of CMIC 40;

Figure 17 illustrates a series of steps which are used to program an FFP;

Figure 18 is a flow chart illustrating the aging process for ARL (L2) and L3 tables; and

5        Figure 19 illustrates communication using a trunk group according to the present invention.

**DETAILED DESCRIPTION OF THE PREFERRED EMBODIMENTS:**

Figure 1 illustrates a configuration wherein a switch-on-chip (SOC) 10, in accordance with the present invention, is functionally connected to external devices 11, external memory 12, fast ethernet ports 13, and gigabit ethernet ports 15. For the purposes of this embodiment, fast ethernet ports 13 will be considered low speed ethernet ports, since they are capable of operating at speeds ranging from 10 Mbps to 100 Mbps, while the gigabit ethernet ports 15, which are high speed ethernet ports, are capable of operating at 1000 Mbps. External devices 11 could include other switching devices for expanding switching capabilities, or other devices as may be required by a particular application. External memory 12 is additional off-chip memory, which is in addition to internal memory which is located on SOC 10, as will be discussed below. CPU 52 can be used as necessary to program SOC 10 with rules which are appropriate to control packet processing. However, once SOC 10 is appropriately programmed or configured, SOC 10 operates, as much as possible, in a free running manner without communicating with CPU 52. Because CPU 52 does not control every aspect of the operation of SOC 10, CPU 52 performance requirements, at least with respect to SOC 10, are fairly low. A less powerful and therefore less expensive CPU 52 can therefore be used when compared to known network switches. As also will be discussed below, SOC 10 utilizes external memory 12 in an efficient manner so that the cost and performance requirements of memory 12 can be reduced. Internal memory on SOC 10, as will be discussed below, is also configured to maximize switching throughput and minimize costs.

It should be noted that any number of fast ethernet ports 13 and gigabit ethernet ports 15 can be provided. In one embodiment, a maximum of 24 fast

ethernet ports 13 and 2 gigabit ports 15 can be provided. Similarly, additional interconnect links to additional external devices 11, external memory 12, and CPUs 52 may be provided as necessary.

Figure 2 illustrates a more detailed block diagram of the functional elements of SOC 10. As evident from Figure 2 and as noted above, SOC 10 includes a plurality of modular systems on-chip, with each modular system, although being on the same chip, being functionally separate from other modular systems. Therefore, each module can efficiently operate in parallel with other modules, and this configuration enables a significant amount of freedom in updating and re-engineering SOC 10.

SOC 10 includes a plurality of Ethernet Port Interface Controllers (EPIC) 20a, 20b, 20c, etc., a plurality of Gigabit Port Interface Controllers (GPIC) 30a, 30b, etc., a CPU Management Interface Controller (CMIC) 40, a Common Buffer Memory Pool (CBP) 50, a Pipelined Memory Management Unit (PMMU) 70, including a Common Buffer Manager (CBM) 71, and a system-wide bus structure referred to as CPS channel 80. The PMMU 70 communicates with external memory 12, which includes a Global Buffer Memory Pool (GBP) 60. The CPS channel 80 comprises C channel 81, P channel 82, and S channel 83. The CPS channel is also referred to as the Cell Protocol Sideband Channel, and is a 17 Gbps channel which glues or interconnects the various modules together. As also illustrated in Figure 2, other high speed interconnects can be provided, as shown as an extendible high speed interconnect. In one embodiment of the invention, this interconnect can be in the form of an interconnect port interface controller (IPIC) 90, which is capable of interfacing CPS channel 80 to external devices 11 through an extendible high speed interconnect link. As will be discussed below, each EPIC 20a, 20b, and 20c, generally referred to as EPIC 20, and GPIC 30a and 30b, generally referred to as GPIC 30, are closely interrelated with appropriate address resolution logic and layer three switching tables 21a, 21b, 21c, 31a, 31b, rules tables 22a, 22b, 22c, 31a, 31b, and VLAN tables 23a, 23b, 23c, 31a, 31b. These tables will be generally referred to as 21, 31,

22, 32, 23, 33, respectively. These tables, like other tables on SOC 10, are implemented in silicon as two-dimensional arrays.

5 In a preferred embodiment of the invention, each EPIC 20 supports 8 fast ethernet ports 13, and switches packets to and/or from these ports as may be appropriate. The ports, therefore, are connected to the network medium (coaxial, twisted pair, fiber, etc.) using known media connection technology, and communicates with the CPS channel 80 on the other side thereof. The interface of each EPIC 20 to the network medium can be provided through a Reduced Media Internal Interface (RMII), which enables  
10 the direct medium connection to SOC 10. As is known in the art, auto-negotiation is an aspect of fast ethernet, wherein the network is capable of negotiating a highest communication speed between a source and a destination based on the capabilities of the respective devices. The communication speed can vary, as noted previously, between 10 Mbps and  
15 100 Mbps; auto negotiation capability, therefore, is built directly into each EPIC module. The address resolution logic (ARL) and layer three tables (ARL/L3) 21a, 21b, 21c, rules table 22a, 22b, 22c, and VLAN tables 23a, 23b, and 23c are configured to be part of or interface with the associated EPIC in an efficient and expedient manner, also to support wirespeed packet flow.

20 Each EPIC 20 has separate ingress and egress functions. On the ingress side, self-initiated and CPU-initiated learning of level 2 address information can occur. Address resolution logic is utilized to assist in this task. Address aging is built in as a feature, in order to eliminate the storage of address information which is no longer valid or useful. The EPIC also  
25 carries out layer 2 mirroring. A fast filtering processor (FFP) 141 (see Fig. 14) is incorporated into the EPIC, in order to accelerate packet forwarding and enhance packet flow. The ingress side of each EPIC and GPIC, illustrated in Figure 8 as ingress submodule 14, has a significant amount of complexity to be able to properly process a significant number of different types of packets  
30 which may come in to the port, for linespeed buffering and then appropriate transfer to the egress. Functionally, each port on each module of SOC 10 has a separate ingress submodule 14 associated therewith. From an

implementation perspective, however, in order to minimize the amount of hardware implemented on the single-chip SOC 10, common hardware elements in the silicon will be used to implement a plurality of ingress submodules on each particular module. The configuration of SOC 10 discussed herein enables concurrent lookups and filtering, and therefore, processing of up to 6.6 million packets per second. Layer two lookups, Layer three lookups and filtering occur simultaneously to achieve this level of performance. On the egress side, the EPIC is capable of supporting packet polling based either as an egress management or class of service (COS) function. Rerouting/scheduling of packets to be transmitted can occur, as well as head-of-line (HOL) blocking notification, packet aging, cell reassembly, and other functions associated with ethernet port interface.

Each GPIC 30 is similar to each EPIC 20, but supports only one gigabit ethernet port, and utilizes a port-specific ARL table, rather than utilizing an ARL table which is shared with any other ports. Additionally, instead of an RMII, each GPIC port interfaces to the network medium utilizing a gigabit media independent interface (GMII).

CMIC 40 acts as a gateway between the SOC 10 and the host CPU. The communication can be, for example, along a PCI bus, or other acceptable communications bus. CMIC 40 can provide sequential direct mapped accesses between the host CPU 52 and the SOC 10. CPU 52, through the CMIC 40, will be able to access numerous resources on SOC 10, including MIB counters, programmable registers, status and control registers, configuration registers, ARL tables, port-based VLAN tables, IEEE 802.1q VLAN tables, layer three tables, rules tables, CBP address and data memory, as well as GBP address and data memory. Optionally, the CMIC 40 can include DMA support, DMA chaining and scatter-gather, as well as master and target PCI64.

Common buffer memory pool or CBP 50 can be considered to be the on-chip data memory. In one embodiment of the invention, the CBP 50 is first level high speed SRAM memory, to maximize performance and minimize hardware overhead requirements. The CBP can have a size of, for example,

720 kilobytes running at 132 MHz. Packets stored in the CBP 50 are typically stored as cells, rather than packets. As illustrated in the figure, PMMU 70 also contains the Common Buffer Manager (CBM) 71 thereupon. CBM 71 handles queue management, and is responsible for assigning cell pointers to incoming cells, as well as assigning common packet IDs (CPID) once the packet is fully written into the CBP. CBM 71 can also handle management of the on-chip free address pointer pool, control actual data transfers to and from the data pool, and provide memory budget management.

Global memory buffer pool or GBP 60 acts as a second level memory, and can be located on-chip or off chip. In the preferred embodiment, GBP 60 is located off chip with respect to SOC 10. When located off-chip, GBP 60 is considered to be a part of or all of external memory 12. As a second level memory, the GBP does not need to be expensive high speed SRAMs, and can be a slower less expensive memory such as DRAM. The GBP is tightly coupled to the PMMU 70, and operates like the CBP in that packets are stored as cells. For broadcast and multicast messages, only one copy of the packet is stored in GBP 60.

As shown in the figure, PMMU 70 is located between GBP 60 and CPS channel 80, and acts as an external memory interface. In order to optimize memory utilization, PMMU 70 includes multiple read and write buffers, and supports numerous functions including global queue management, which broadly includes assignment of cell pointers for rerouted incoming packets, maintenance of the global FAP, time-optimized cell management, global memory budget management, GPID assignment and egress manager notification, write buffer management, read prefetches based upon egress manager/class of service requests, and smart memory control.

As shown in Figure 2, the CPS channel 80 is actually three separate channels, referred to as the C-channel, the P-channel, and the S-channel. The C-channel is 128 bits wide, and runs at 132 MHz. Packet transfers between ports occur on the C-channel. Since this channel is used solely for data transfer, there is no overhead associated with its use. The P-channel or protocol channel is synchronous or locked with the C-channel. During cell

transfers, the message header is sent via the P-channel by the PMMU. The P-channel is 32 bits wide, and runs at 132 MHz.

5 The S or sideband channel runs at 132 MHz, and is 32 bits wide. The S-channel is used for functions such as conveying Port Link Status, receive port full, port statistics, ARL table synchronization, memory and register access to CPU and other CPU management functions, and global memory full and common memory full notification.

10 A proper understanding of the operation of SOC 10 requires a proper understanding of the operation of CPS channel 80. Referring to Figure 3, it can be seen that in SOC 10, on the ingress, packets are sliced by an EPIC 20 or GPIC 30 into 64-byte cells. The use of cells on-chip instead of packets makes it easier to adapt the SOC to work with cell based protocols such as, for example, Asynchronous Transfer Mode (ATM). Presently, however, ATM utilizes cells which are 53 bytes long, with 48 bytes for payload and 5 bytes for header. In the SOC, incoming packets are sliced into cells which are 64 bytes long as discussed above, and the cells are further divided into four separate 16 byte cell blocks Cn0...Cn3. Locked with the C-channel is the P-channel, which locks the opcode in synchronization with Cn0. A port bit map is inserted into the P-channel during the phase Cn1. The untagged bit map is inserted into the P-channel during phase Cn2, and a time stamp is placed on the P-channel in Cn3. Independent from occurrences on the C and P-channel, the S-channel is used as a sideband, and is therefore decoupled from activities on the C and P-channel.

#### **Cell or C-Channel**

25 Arbitration for the CPS channel occurs out of band. Every module (EPIC, GPIC, etc.) monitors the channel, and matching destination ports respond to appropriate transactions. C-channel arbitration is a demand priority round robin arbitration mechanism. If no requests are active, however, the default module, which can be selected during the configuration of SOC 10, can park on the channel and have complete access thereto. If all requests are active, the configuration of SOC 10 is such that the PMMU is granted access every other cell cycle, and EPICs 20 and GPICs 30 share equal

30

access to the C-channel on a round robin basis. Figures 4A and 4B illustrate a C-channel arbitration mechanism wherein section A is the PMMU, and section B consists of two GPICs and three EPICs. The sections alternate access, and since the PMMU is the only module in section A, it gains access every other cycle. The modules in section B, as noted previously, obtain access on a round robin basis.

#### Protocol or P-Channel

Referring once again to the protocol or P-channel, a plurality of messages can be placed on the P-channel in order to properly direct flow of data flowing on the C-channel. Since P-channel 82 is 32 bits wide, and a message typically requires 128 bits, four smaller 32 bit messages are put together in order to form a complete P-channel message. The following list identifies the fields and function and the various bit counts of the 128 bit message on the P-channel.

- 15       **Opcode** - 2 bits long - Identifies the type of message present on the C channel 81;
- IP Bit** - 1 bit long - This bit is set to indicate that the packet is an IP switched packet;
- IPX Bit** - 1 bit long - This bit is set to indicate that the packet is an IPX switched packet;
- 20       **Next Cell** - 2 bits long - A series of values to identify the valid bytes in the corresponding cell on the C channel 81;
- SRC DEST Port** - 6 bits long - Defines the port number which sends the message or receives the message, with the interpretation of the source or destination depending upon Opcode;
- 25       **Cos** - 3 bits long - Defines class of service for the current packet being processed;
- J** - 1 bit long - Describes whether the current packet is a jumbo packet;
- S** - 1 bit long - Indicates whether the current cell is the first cell of the packet;
- 30       **E** - 1 bit long - Indicates whether the current cell is the last cell of the packet;

**CRC** - 2 bits long - Indicates whether a Cyclical Redundancy Check (CRC) value should be appended to the packet and whether a CRC value should be regenerated;

**P Bit** - 1 bit long - Determines whether MMU should Purge the entire packet;

**Len** - 7 bytes - Identifies the valid number of bytes in current transfer;

**O** - 2 bits - Defines an optimization for processing by the CPU 52; and

**Bc/Mc Bitmap** - 28 bits - Defines the broadcast or multicast bitmap. Identifies egress ports to which the packet should be set, regarding multicast and broadcast messages.

**Untag Bits/Source Port** - 28/5 bits long - Depending upon Opcode, the packet is transferred from Port to MMU, and this field is interpreted as the untagged bit map. A different Opcode selection indicates that the packet is being transferred from MMU to egress port, and the last six bits of this field is interpreted as the Source Port field. The untagged bits identifies the egress ports which will strip the tag header, and the source port bits identifies the port number upon which the packet has entered the switch;

**U Bit** - 1 bit long - For a particular Opcode selection (0x01, this bit being set indicates that the packet should leave the port as Untagged; in this case, tag stripping is performed by the appropriate MAC;

**CPU Opcode** - 18 bits long - These bits are set if the packet is being sent to the CPU for any reason. Opcodes are defined based upon filter match, learn bits being set, routing bits, destination lookup failure (DLF), station movement, etc;

**Time Stamp** - 14 bits - The system puts a time stamp in this field when the packet arrives, with a granularity of 1  $\mu$ sec.

The opcode field of the P-channel message defines the type of message currently being sent. While the opcode is currently shown as having a width of 2 bits, the opcode field can be widened as desired to account for new types of messages as may be defined in the future. Graphically, however, the P-channel message type defined above is shown in Figure 5.

An early termination message is used to indicate to CBM 71 that the current packet is to be terminated. During operation, as discussed in more detail below, the status bit (S) field in the message is set to indicate the desire to purge the current packet from memory. Also in response to the status bit  
5 all applicable egress ports would purge the current packet prior to transmission.

The Src Dest Port field of the P-channel message, as stated above, define the destination and source port addresses, respectively. Each field is 6 bits wide and therefore allows for the addressing of sixty-four ports.

10 The CRC field of the message is two bits wide and defines CRC actions. Bit 0 of the field provides an indication whether the associated egress port should append a CRC to the current packet. An egress port would append a CRC to the current packet when bit 0 of the CRC field is set to a logical one. Bit 1 of the CRC field provides an indication whether the  
15 associated egress port should regenerate a CRC for the current packet. An egress port would regenerate a CRC when bit 1 of the CRC field is set to a logical one. The CRC field is only valid for the last cell transmitted as defined by the E bit field of P-channel message set to a logical one.

As with the CRC field, the status bit field (st), the Len field, and the Cell  
20 Count field of the message are only valid for the last cell of a packet being transmitted as defined by the E bit field of the message.

Last, the time stamp field of the message has a resolution of 1  $\mu$ s and is valid only for the first cell of the packet defined by the S bit field of the message. A cell is defined as the first cell of a received packet when the S  
25 bit field of the message is set to a logical one value.

As is described in more detail below, the C channel 81 and the P channel 82 are synchronously tied together such that data on C channel 81 is transmitted over the CPS channel 80 while a corresponding P channel message is simultaneously transmitted.

### 30 **S-Channel or Sideband Channel**

The S channel 83 is a 32-bit wide channel which provides a separate communication path within the SOC 10. The S channel 83 is used for

management by CPU 52, SOC 10 internal flow control, and SOC 10 inter-module messaging. The S channel 83 is a sideband channel of the CPS channel 80, and is electrically and physically isolated from the C channel 81 and the P channel 82. It is important to note that since the S channel is  
5 separate and distinct from the C channel 81 and the P channel 82, operation of the S channel 83 can continue without performance degradation related to the C channel 81 and P channel 82 operation. Conversely, since the C channel is not used for the transmission of system messages, but rather only data, there is no overhead associated with the C channel 81 and, thus, the C  
10 channel 81 is able to free-run as needed to handle incoming and outgoing packet information.

The S channel 83 of CPS channel 80 provides a system wide communication path for transmitting system messages, for example, providing the CPU 52 with access to the control structure of the SOC 10. System  
15 messages include port status information, including port link status, receive, port full, and port statistics, ARL table 22 synchronization, CPU 52 access to GBP 60 and CBP 50 memory buffers and SOC 10 control registers, and memory full notification corresponding to GBP 60 and/or CBP 50.

Figure 6 illustrates a message format for an S channel message on S  
20 channel 83. The message is formed of four 32-bit words; the bits of the fields of the words are defined as follows:

- Opcode** - 6 bits long - Identifies the type of message present on the S channel;
- Dest Port** - 6 bits long - Defines the port number to which the current  
25 S channel message is addressed;
- Src Port** - 6 bits long - Defines the port number of which the current S channel message originated;
- COS** - 3 bits long - Defines the class of service associated with the current S channel message; and
- C bit** - 1 bit long - Logically defines whether the current S channel  
30 message is intended for the CPU 52.
- Error Code** - 2 bits long - Defines a valid error when the **E bit** is set;

**DataLen** - 7 bits long - Defines the total number of data bytes in the **Data** field;

**E bit** - 1 bit long - Logically indicates whether an error has occurred in the execution of the current command as defined by **opcode**;

5      **Address** - 32 bits long - Defines the memory address associated with the current command as defined in **opcode**;

**Data** - 0-127 bits long - Contains the data associated with the current **opcode**.

10      With the configuration of CPS channel 80 as explained above, the decoupling of the S channel from the C channel and the P channel is such that the bandwidth on the C channel can be preserved for cell transfer, and that overloading of the C channel does not affect communications on the sideband channel.

#### **SOC Operation**

15      The configuration of the SOC 10 supports fast ethernet ports, gigabit ports, and extendible interconnect links as discussed above. The SOC configuration can also be "stacked", thereby enabling significant port expansion capability. Once data packets have been received by SOC 10, sliced into cells, and placed on CPS channel 80, stacked SOC modules can  
20      interface with the CPS channel and monitor the channel, and extract appropriate information as necessary. As will be discussed below, a significant amount of concurrent lookups and filtering occurs as the packet comes in to ingress submodule 14 of an EPIC 20 or GPIC 30, with respect to layer two and layer three lookups, and fast filtering.

25      Now referring to Figs. 8 and 9, the handling of a data packet is described. For explanation purposes, ethernet data to be received will consider to arrive at one of the ports 24a of EPIC 20a. It will be presumed that the packet is intended to be transmitted to a user on one of ports 24c of EPIC 20c. All EPICs 20 (20a, 20b, 20c, etc.) have similar features and  
30      functions, and each individually operate based on packet flow.

An input data packet 112 is applied to the port 24a is shown. The data packet 112 is, in this example, defined per the current standards for 10/100

Mbps Ethernet transmission and may have any length or structure as defined by that standard. This discussion will assume the length of the data packet 112 to be 1024 bits or 128 bytes.

When the data packet 112 is received by the EPIC module 20a, an  
5 ingress sub-module 14a, as an ingress function, determines the destination of the packet 112. The first 64 bytes of the data packet 112 is buffered by the ingress sub-module 14a and compared to data stored in the lookup tables 21a to determine the destination port 24c. Also as an ingress function, the  
10 ingress sub-module 14a slices the data packet 112 into a number of 64-byte cells; in this case, the 128 byte packet is sliced in two 64 byte cells 112a and 112b. While the data packet 112 is shown in this example to be exactly two 64-byte cells 112a and 112b, an actual incoming data packet may include any number of cells, with at least one cell of a length less than 64 bytes. Padding  
15 bytes are used to fill the cell. In such cases the ingress sub-module 14a disregards the padding bytes within the cell. Further discussions of packet handling will refer to packet 112 and/or cells 112a and 112b.

It should be noted that each EPIC 20 (as well as each GPIC 30) has an ingress submodule 14 and egress submodule 16, which provide port specific ingress and egress functions. All incoming packet processing occurs  
20 in ingress submodule 14, and features such as the fast filtering processor, layer two (L2) and layer three (L3) lookups, layer two learning, both self-initiated and CPU 52 initiated, layer two table management, layer two switching, packet slicing, and channel dispatching occurs in ingress submodule 14. After lookups, fast filter processing, and slicing into cells, as  
25 noted above and as will be discussed below, the packet is placed from ingress submodule 14 into dispatch unit 18, and then placed onto CPS channel 80 and memory management is handled by PMMU 70. A number of ingress buffers are provided in dispatch unit 18 to ensure proper handling of the packets/cells. Once the cells or cellularized packets are placed onto the  
30 CPS channel 80, the ingress submodule is finished with the packet. The ingress is not involved with dynamic memory allocation, or the specific path the cells will take toward the destination. Egress submodule 16, illustrated in

Figure 8 as submodule 16a of EPIC 20a, monitors CPS channel 80 and continuously looks for cells destined for a port of that particular EPIC 20. When the PMMU 70 receives a signal that an egress associated with a destination of a packet in memory is ready to receive cells, PMMU 70 pulls  
5 the cells associated with the packet out of the memory, as will be discussed below, and places the cells on CPS channel 80, destined for the appropriate egress submodule. A FIFO in the egress submodule 16 continuously sends a signal onto the CPS channel 80 that it is ready to receive packets, when there is room in the FIFO for packets or cells to be received. As noted  
10 previously, the CPS channel 80 is configured to handle cells, but cells of a particular packet are always handled together to avoid corrupting of packets.

In order to overcome data flow degradation problems associated with overhead usage of the C channel 81, all L2 learning and L2 table management is achieved through the use of the S channel 83. L2 self-  
15 initiated learning is achieved by deciphering the source address of a user at a given ingress port 24 utilizing the packet's associated address. Once the identity of the user at the ingress port 24 is determined, the ARL/L3 tables 21a are updated to reflect the user identification. The ARL/L3 tables 21 of each other EPIC 20 and GPIC 30 are updated to reflect the newly acquired  
20 user identification in a synchronizing step, as will be discussed below. As a result, while the ingress of EPIC 20a may determine that a given user is at a given port 24a, the egress of EPIC 20b, whose table 21b has been updated with the user's identification at port 24a, can then provide information to the User at port 24a without re-learning which port the user was connected.

25 Table management may also be achieved through the use of the CPU 52. CPU 52, via the CMIC 40, can provide the SOC 10 with software functions which result in the designation of the identification of a user at a given port 24. As discussed above, it is undesirable for the CPU 52 to access the packet information in its entirety since this would lead to performance  
30 degradation. Rather, the SOC 10 is programmed by the CPU 52 with identification information concerning the user. The SOC 10 can maintain real-time data flow since the table data communication between the CPU 52 and

the SOC 10 occurs exclusively on the S channel 83. While the SOC 10 can provide the CPU 52 with direct packet information via the C channel 81, such a system setup is undesirable for the reasons set forth above. As stated above, as an ingress function an address resolution lookup is performed by examining the ARL table 21a. If the packet is addressed to one of the layer three (L3) switches of the SOC 10, then the ingress sub-module 14a performs the L3 and default table lookup. Once the destination port has been determined, the EPIC 20a sets a ready flag in the dispatch unit 18a which then arbitrates for C channel 81.

The C channel 81 arbitration scheme, as discussed previously and as illustrated in Figures 4A and 4B, is Demand Priority Round-Robin. Each I/O module, EPIC 20, GPIC 30, and CMIC 40, along with the PMMU 70, can initiate a request for C channel access. If no requests exist at any one given time, a default module established with a high priority gets complete access to the C channel 81. If any one single I/O module or the PMMU 70 requests C channel 81 access, that single module gains access to the C channel 81 on-demand.

If EPIC modules 20a, 20b, 20c, and GPIC modules 30a and 30b, and CMIC 40 simultaneously request C channel access, then access is granted in round-robin fashion. For a given arbitration time period each of the I/O modules would be provided access to the C channel 81. For example, each GPIC module 30a and 30b would be granted access, followed by the EPIC modules, and finally the CMIC 40. After every arbitration time period the next I/O module with a valid request would be given access to the C channel 81. This pattern would continue as long as each of the I/O modules provide an active C channel 81 access request.

If all the I/O modules, including the PMMU 70, request C channel 81 access, the PMMU 70 is granted access as shown in Fig. 4B since the PMMU provides a critical data path for all modules on the switch. Upon gaining access to the channel 81, the dispatch unit 18a proceeds in passing the received packet 112, one cell at a time, to C channel 81.

Referring again to Figure 3, the individual C, P, and S channels of the CPS channel 80 are shown. Once the dispatch unit 18a has been given permission to access the CPS channel 80, during the first time period Cn0, the dispatch unit 18a places the first 16 bytes of the first cell 112a of the received packet 112 on the C channel 81. Concurrently, the dispatch unit 18a places the first P channel message corresponding to the currently transmitted cell. As stated above, the first P channel message defines, among other things, the message type. Therefore, this example is such that the first P channel message would define the current cell as being a unicast type message to be directed to the destination egress port 21c.

During the second clock cycle Cn1, the second 16 bytes (16:31) of the currently transmitted data cell 112a are placed on the C channel 81. Likewise, during the second clock cycle Cn1, the Bc/Mc Port Bitmap is placed on the P channel 82.

As indicated by the hatching of the S channel 83 data during the time periods Cn0 to Cn3 in Fig. 3, the operation of the S channel 83 is decoupled from the operation of the C channel 81 and the P channel 82. For example, the CPU 52, via the CMIC 40, can pass system level messages to non-active modules while an active module passes cells on the C channel 81. As previously stated, this is an important aspect of the SOC 10 since the S channel operation allows parallel task processing, permitting the transmission of cell data on the C channel 81 in real-time. Once the first cell 112a of the incoming packet 112 is placed on the CPS channel 80 the PMMU 70 determines whether the cell is to be transmitted to an egress port 21 local to the SOC 10.

If the PMMU 70 determines that the current cell 112a on the C channel 81 is destined for an egress port of the SOC 10, the PMMU 70 takes control of the cell data flow.

Figure 10 illustrates, in more detail, the functional egress aspects of PMMU 70. PMMU 70 includes CBM 71, and interfaces between the GBP, CBP and a plurality of egress managers (EgM) 76 of egress submodule 18, with one egress manager 76 being provided for each egress port. CBM 71

is connected to each egress manager 76, in a parallel configuration, via R channel data bus 77. R channel data bus 77 is a 32-bit wide bus used by CBM 71 and egress managers 76 in the transmission of memory pointers and system messages. Each egress manager 76 is also connected to CPS channel 80, for the transfer of data cells 112a and 112b.

CBM 71, in summary, performs the functions of on-chip FAP (free address pool) management, transfer of cells to CBP 50, packet assembly and notification to the respective egress managers, rerouting of packets to GBP 60 via a global buffer manager, as well as handling packet flow from the GBP 60 to CBP 50. Memory clean up, memory budget management, channel interface, and cell pointer assignment are also functions of CBM 71. With respect to the free address pool, CBM 71 manages the free address pool and assigns free cell pointers to incoming cells. The free address pool is also written back by CBM 71, such that the released cell pointers from various egress managers 76 are appropriately cleared. Assuming that there is enough space available in CBP 50, and enough free address pointers available, CBM 71 maintains at least two cell pointers per egress manager 76 which is being managed. The first cell of a packet arrives at an egress manager 76, and CBM 71 writes this cell to the CBM memory allocation at the address pointed to by the first pointer. In the next cell header field, the second pointer is written. The format of the cell as stored in CBP 50 is shown in Figure 11; each line is 18 bytes wide. Line 0 contains appropriate information with respect to first cell and last cell information, broadcast/multicast, number of egress ports for broadcast or multicast, cell length regarding the number of valid bytes in the cell, the next cell pointer, total cell count in the packet, and time stamp. The remaining lines contain cell data as 64 byte cells. The free address pool within PMMU 70 stores all free pointers for CBP 50. Each pointer in the free address pool points to a 64-byte cell in CBP 50; the actual cell stored in the CBP is a total of 72 bytes, with 64 bytes being byte data, and 8 bytes of control information. Functions such as HOL blocking high and low watermarks, out queue budget registers, CPID assignment, and other functions are handled in CBM 71, as explained herein.

When PMMU 70 determines that cell 112a is destined for an appropriate egress port on SOC 10, PMMU 70 controls the cell flow from CPS channel 80 to CBP 50. As the data packet 112 is received at PMMU 70 from CPS 80, CBM 71 determines whether or not sufficient memory is available in CBP 50 for the data packet 112. A free address pool (not shown) can provide storage for at least two cell pointers per egress manager 76, per class of service. If sufficient memory is available in CBP 50 for storage and identification of the incoming data packet, CBM 71 places the data cell information on CPS channel 80. The data cell information is provided by CBM 71 to CBP 50 at the assigned address. As new cells are received by PMMU 70, CBM 71 assigns cell pointers. The initial pointer for the first cell 112a points to the egress manager 76 which corresponds to the egress port to which the data packet 112 will be sent after it is placed in memory. In the example of Figure 8, packets come in to port 24a of EPIC 20a, and are destined for port 24c of EPIC 20c. For each additional cell 112b, CBM 71 assigns a corresponding pointer. This corresponding cell pointer is stored as a two byte or 16 bit value NC\_header, in an appropriate place on a control message, with the initial pointer to the corresponding egress manager 76, and successive cell pointers as part of each cell header, a linked list of memory pointers is formed which defines packet 112 when the packet is transmitted via the appropriate egress port, in this case 24c. Once the packet is fully written into CBP 50, a corresponding CBP Packet Identifier (CPID) is provided to the appropriate egress manager 76; this CPID points to the memory location of initial cell 112a. The CPID for the data packet is then used when the data packet 112 is sent to the destination egress port 24c. In actuality, the CBM 71 maintains two buffers containing a CBP cell pointer, with admission to the CBP being based upon a number of factors. An example of admission logic for CBP 50 will be discussed below with reference to Figure 12.

Since CBM 71 controls data flow within SOC 10, the data flow associated with any ingress port can likewise be controlled. When packet 112 has been received and stored in CBP 50, a CPID is provided to the

associated egress manager 76. The total number of data cells associated with the data packet is stored in a budget register (not shown). As more data packets 112 are received and designated to be sent to the same egress manager 76, the value of the budget register corresponding to the associated egress manager 76 is incremented by the number of data cells 112a, 112b of the new data cells received. The budget register therefore dynamically represents the total number of cells designated to be sent by any specific egress port on an EPIC 20. CBM 71 controls the inflow of additional data packets by comparing the budget register to a high watermark register value or a low watermark register value, for the same egress.

When the value of the budget register exceeds the high watermark value, the associated ingress port is disabled. Similarly, when data cells of an egress manager 76 are sent via the egress port, and the corresponding budget register decreases to a value below the low watermark value, the ingress port is once again enabled. When egress manager 76 initiates the transmission of packet 112, egress manager 76 notifies CBM 71, which then decrements the budget register value by the number of data cells which are transmitted. The specific high watermark values and low watermark values can be programmed by the user via CPU 52. This gives the user control over the data flow of any port on any EPIC 20 or GPIC 30.

Egress manager 76 is also capable of controlling data flow. Each egress manager 76 is provided with the capability to keep track of packet identification information in a packet pointer budget register; as a new pointer is received by egress manager 76, the associated packet pointer budget register is incremented. As egress manager 76 sends out a data packet 112, the packet pointer budget register is decremented. When a storage limit assigned to the register is reached, corresponding to a full packet identification pool, a notification message is sent to all ingress ports of the SOC 10, indicating that the destination egress port controlled by that egress manager 76 is unavailable. When the packet pointer budget register is decremented below the packet pool high watermark value, a notification

message is sent that the destination egress port is now available. The notification messages are sent by CBM 71 on the S channel 83.

As noted previously, flow control may be provided by CBM 71, and also by ingress submodule 14 of either an EPIC 20 or GPIC 30. Ingress submodule 14 monitors cell transmission into ingress port 24. When a data packet 112 is received at an ingress port 24, the ingress submodule 14 increments a received budget register by the cell count of the incoming data packet. When a data packet 112 is sent, the corresponding ingress 14 decrements the received budget register by the cell count of the outgoing data packet 112. The budget register 72 is decremented by ingress 14 in response to a decrement cell count message initiated by CBM 71, when a data packet 112 is successfully transmitted from CBP 50.

Efficient handling of the CBP and GBP is necessary in order to maximize throughput, to prevent port starvation, and to prevent port underrun. For every ingress, there is a low watermark and a high watermark; if cell count is below the low watermark, the packet is admitted to the CBP, thereby preventing port starvation by giving the port an appropriate share of CBP space.

Figure 12 generally illustrates the handling of a data packet 112 when it is received at an appropriate ingress port. This figure illustrates dynamic memory allocation on a single port, and is applicable for each ingress port. In step 12-1, packet length is estimated by estimating cell count based upon egress manager count plus incoming cell count. After this cell count is estimated, the GBP current cell count is checked at step 12-2 to determine whether or not the GBP 60 is empty. If the GBP cell count is 0, indicating that GBP 60 is empty, the method proceeds to step 12-3, where it is determined whether or not the estimated cell count from step 12-1 is less than the admission low watermark. The admission low watermark value enables the reception of new packets 112 into CBP 50 if the total number of cells in the associated egress is below the admission low watermark value. If yes, therefore, the packet is admitted at step 12-5. If the estimated cell count is not below the admission low watermark, CBM 71 then arbitrates for CBP

memory allocation with other ingress ports of other EPICs and GPICs, in step 12-4. If the arbitration is unsuccessful, the incoming packet is sent to a reroute process, referred to as A. If the arbitration is successful, then the packet is admitted to the CBP at step 12-5. Admission to the CBP is  
5 necessary for linespeed communication to occur.

The above discussion is directed to a situation wherein the GBP cell count is determined to be 0. If in step 12-2 the GBP cell count is determined not to be 0, then the method proceeds to step 12-6, where the estimated cell count determined in step 12-1 is compared to the admission high watermark.  
10 If the answer is no, the packet is rerouted to GBP 60 at step 12-7. If the answer is yes, the estimated cell count is then compared to the admission low watermark at step 12-8. If the answer is no, which means that the estimated cell count is between the high watermark and the low watermark, then the packet is rerouted to GBP 60 at step 12-7. If the estimated cell count is below  
15 the admission low watermark, the GBP current count is compared with a reroute cell limit value at step 12-9. This reroute cell limit value is user programmable through CPU 52. If the GBP count is below or equal to the reroute cell limit value at step 12-9, the estimated cell count and GBP count are compared with an estimated cell count low watermark; if the combination  
20 of estimated cell count and GBP count are less than the estimated cell count low watermark, the packet is admitted to the CBP. If the sum is greater than the estimated cell count low watermark, then the packet is rerouted to GBP 60 at step 12-7. After rerouting to GBP 60, the GBP cell count is updated, and the packet processing is finished. It should be noted that if both the CBP  
25 and the GBP are full, the packet is dropped. Dropped packets are handled in accordance with known ethernet or network communication procedures, and have the effect of delaying communication. However, this configuration applies appropriate back pressure by setting watermarks, through CPU 52, to appropriate buffer values on a per port basis to maximize memory  
30 utilization. This CBP/GBP admission logic results in a distributed hierarchical shared memory configuration, with a hierarchy between CBP 50 and GBP 60, and hierarchies within the CBP.

### Address Resolution (L2) + (L3)

Figure 14 illustrates some of the concurrent filtering and look-up details of a packet coming into the ingress side of an EPIC 20. Figure 12, as discussed previously, illustrates the handling of a data packet with respect to admission into the distributed hierarchical shared memory. Figure 14 addresses the application of filtering, address resolution, and rules application segments of SOC 10. These functions are performed simultaneously with respect to the CBP admission discussed above. As shown in the figure, packet 112 is received at input port 24 of EPIC 20. It is then directed to input FIFO 142. As soon as the first sixteen bytes of the packet arrive in the input FIFO 142, an address resolution request is sent to ARL engine 143; this initiates lookup in ARL/L3 tables 21.

A description of the fields of an ARL table of ARL/L3 tables 21 is as follows:

- 15        **Mac Address** - 48 bits long - Mac Address;
- VLAN tag** - 12 bits long - VLAN Tag Identifier as described in IEEE 802.1q standard for tagged packets. For an untagged Packet, this value is picked up from Port Based VLAN Table.
- CosDst** - 3 bits long - Class of Service based on the Destination
- 20        Address. COS identifies the priority of this packet. 8 levels of priorities as described in IEEE 802.1p standard.
- Port Number** - 6 bits long - Port Number is the port on which this Mac address is learned.
- SD\_Disc Bits** - 2 bits long - These bits identifies whether the packet
- 25        should be discarded based on Source Address or Destination Address. Value 1 means discard on source. Value 2 means discard on destination.
- C bit** - 1 bit long - C Bit identifies that the packet should be given to CPU Port.
- 30        **St Bit** - 1 bit long - St Bit identifies that this is a static entry (it is not learned Dynamically) and that means is should not be aged out. Only CPU 52 can delete this entry.

**Ht Bit** - 1 bit long - Hit Bit-This bit is set if there is match with the Source Address. It is used in the aging Mechanism.

**CosSrc** - 3 bits long - Class of Service based on the Source Address. COS identifies the priority of this packet.

5      **L3 Bit** - 1 bit long - L3 Bit - identifies that this entry is created as result of L3 Interface Configuration. The Mac address in this entry is L3 interface Mac Address and that any Packet addresses to this Mac Address need to be routed.

10      **T Bit** - 1 bit long - T Bit identifies that this Mac address is learned from one of the Trunk Ports. If there is a match on Destination address then output port is not decided on the Port Number in this entry, but is decided by the Trunk Identification Process based on the rules identified by the RTAG bits and the Trunk group Identified by the TGID.

15      **TGID** - 3 bits long - TGID identifies the Trunk Group if the T Bit is set. SOC 10 supports 6 Trunk Groups per switch.

20      **RTAG** - 3 bits long - RTAG identifies the Trunk selection criterion if the destination address matches this entry and the T bit is set in that entry. Value 1 - based on Source Mac Address. Value 2 - based on Destination Mac Address. Value 3 - based on Source & destination Address. Value 4 - based on Source IP Address. Value 5 - based on Destination IP Address. Value 6 - based on Source and Destination IP Address.

25      **S C P** - 1 bit long - Source CoS Priority Bit - If this bit is set (in the matched Source Mac Entry) then Source CoS has priority over Destination Cos.

30      It should also be noted that VLAN tables 23 include a number of table formats; all of the tables and table formats will not be discussed here. However, as an example, the port based VLAN table fields are described as follows:

**Port VLAN Id** - 12 bits long - Port VLAN Identifier is the VLAN Id used by Port Based VLAN.

5       **Sp State** - 2 bits long - This field identifies the current Spanning Tree State. Value 0x00 - Port is in Disable State. No packets are accepted in this state, not even BPDUs. Value 0x01 - Port is in Blocking or Listening State. In this state no packets are accepted by the port, except BPDUs. Value 0x02 - Port is in Learning State. In this state the packets are not forwarded to another Port but are accepted for learning. Value 0x03 - Port is in Forwarding State. In this state the packets are accepted both for learning and forwarding.

10       **Port Discard Bits** - 6 bits long - There are 6 bits in this field and each bit identifies the criterion to discard the packets coming in this port. Note: Bits 0 to 3 are not used. Bit 4 - If this bit is set then all the frames coming on this port will be discarded. Bit 5 - If this bit is set then any 802.1q Priority Tagged (vid = 0) and Untagged frame coming on this port will be discarded.

15       **J Bit** - 1 bit long - J Bit means Jumbo bit. If this bit is set then this port should accept Jumbo Frames.

20       **RTAG** - 3 bits long - RTAG identifies the Trunk selection criterion if the destination address matches this entry and the T bit is set in that entry. Value 1 - based on Source Mac Address. Value 2 - based on Destination Mac Address. Value 3 - based on Source & destination Address. Value 4 - based on Source IP Address. Value 5 - based on Destination IP Address. Value 6 - based on Source and Destination IP Address.

25       **T Bit** - 1 bit long - This bit identifies that the Port is a member of the Trunk Group.

**C Learn Bit** - 1 bit long - Cpu Learn Bit - If this bit is set then the packet is send to the CPU whenever the source Address is learned.

**PT** - 2 bits long - Port Type identifies the port Type. Value 0 -10 Mbit Port. Value 1-100 Mbit Port. Value 2-1Gbit Port. Value 3-CPU Port.

30       **VLAN Port Bitmap** - 28 bits long - VLAN Port Bitmap Identifies all the egress ports on which the packet should go out.

**B Bit** - 1 bit long - B bit is BPDU bit. If this bit is set then the Port rejects BPDUs. This Bit is set for Trunk Ports which are not supposed to accept BPDUs.

5        **TGID** - 3 bits long - TGID - this field identifies the Trunk Group which this port belongs to.

**Untagged Bitmap** - 28 bits long - This bitmap identifies the Untagged Members of the VLAN. i.e. if the frame destined out of these members ports should be transmitted without Tag Header.

10       **M Bits** - 1 bit long - M Bit is used for Mirroring Functionality. If this bit is set then mirroring on Ingress is enabled.

The ARL engine 143 reads the packet; if the packet has a VLAN tag according to IEEE Standard 802.1q, then ARL engine 143 performs a look-up based upon tagged VLAN table 231, which is part of VLAN table 23. If the packet does not contain this tag, then the ARL engine performs VLAN lookup based upon the port based VLAN table 232. Once the VLAN is identified for the incoming packet, ARL engine 143 performs an ARL table search based upon the source MAC address and the destination MAC address. If the results of the destination search is an L3 interface MAC address, then an L3 search is performed of an L3 table within ARL/L3 table 21. If the L3 search is successful, then the packet is modified according to packet routing rules.

20       To better understand lookups, learning, and switching, it may be advisable to once again discuss the handling of packet 112 with respect to Figure 8. If data packet 112 is sent from a source station A into port 24a of EPIC 20a, and destined for a destination station B on port 24c of EPIC 20c, ingress submodule 14a slices data packet 112 into cells 112a and 112b. The ingress submodule then reads the packet to determine the source MAC address and the destination MAC address. As discussed previously, ingress submodule 14a, in particular ARL engine 143, performs the lookup of appropriate tables within ARL/L3 tables 21a, and VLAN table 23a, to see if the destination MAC address exists in ARL/L3 tables 21a; if the address is not found, but if the VLAN IDs are the same for the source and destination, then ingress submodule 14a will set the packet to be sent to all ports. The packet

will then propagate to the appropriate destination address. A "source search" and a "destination search" occurs in parallel. Concurrently, the source MAC address of the incoming packet is "learned", and therefore added to an ARL table within ARL/L3 table 21a. After the packet is received by the destination,

5 an acknowledgement is sent by destination station B to source station A. Since the source MAC address of the incoming packet is learned by the appropriate table of B, the acknowledgement is appropriately sent to the port on which A is located. When the acknowledgement is received at port 24a, therefore, the ARL table learns the source MAC address of B from the

10 acknowledgement packet. It should be noted that as long as the VLAN IDs (for tagged packets) of source MAC addresses and destination MAC addresses are the same, layer two switching as discussed above is performed. L2 switching and lookup is therefore based on the first 16 bytes of an incoming packet. For untagged packets, the port number field in the

15 packet is indexed to the port-based VLAN table within VLAN table 23a, and the VLAN ID can then be determined. If the VLAN IDs are different, however, L3 switching is necessary wherein the packets are sent to a different VLAN. L3 switching, however, is based on the IP header field of the packet. The IP header includes source IP address, destination IP address, and TTL (time-to-

20 live).

In order to more clearly understand layer three switching according to the invention, data packet 112 is sent from source station A onto port 24a of EPIC 20a, and is directed to destination station B; assume, however, that station B is disposed on a different VLAN, as evidenced by the source MAC

25 address and the destination MAC address having differing VLAN IDs. The lookup for B would be unsuccessful since B is located on a different VLAN, and merely sending the packet to all ports on the VLAN would result in B never receiving the packet. Layer three switching, therefore, enables the bridging of VLAN boundaries, but requires reading of more packet information

30 than just the MAC addresses of L2 switching. In addition to reading the source and destination MAC addresses, therefore, ingress 14a also reads the IP address of the source and destination. As noted previously, packet types

are defined by IEEE and other standards, and are known in the art. By reading the IP address of the destination, SOC 10 is able to target the packet to an appropriate router interface which is consistent with the destination IP address. Packet 112 is therefore sent on to CPS channel 80 through dispatch unit 18a, destined for an appropriate router interface (not shown, and not part of SOC 10), upon which destination B is located. Control frames, identified as such by their destination address, are sent to CPU 52 via CMIC 40. The destination MAC address, therefore, is the router MAC address for B. The router MAC address is learned through the assistance of CPU 52, which uses an ARP (address resolution protocol) request to request the destination MAC address for the router for B, based upon the IP address of B. Through the use of the IP address, therefore, SOC 10 can learn the MAC address. Through the acknowledgement and learning process, however, it is only the first packet that is subject to this "slow" handling because of the involvement of CPU 52. After the appropriate MAC addresses are learned, linespeed switching can occur through the use of concurrent table lookups since the necessary information will be learned by the tables. Implementing the tables in silicon as two-dimensional arrays enables such rapid concurrent lookups. Once the MAC address for B has been learned, therefore, when packets come in with the IP address for B, ingress 14a changes the IP address to the destination MAC address, in order to enable linespeed switching. Also, the source address of the incoming packet is changed to the router MAC address for A rather than the IP address for A, so that the acknowledgement from B to A can be handled in a fast manner without needing to utilize a CPU on the destination end in order to identify the source MAC address to be the destination for the acknowledgement. Additionally, a TTL (time-to-live) field in the packet is appropriately manipulated in accordance with the IETF (Internet Engineering Task Force) standard. A unique aspect of SOC 10 is that all of the switching, packet processing, and table lookups are performed in hardware, rather than requiring CPU 52 or another CPU to spend time processing instructions. It should be noted that the layer three tables for EPIC 20 can have varying sizes; in a preferred embodiment, these tables are

capable of holding up to 2000 addresses, and are subject to purging and deletion of aged addresses, as explained herein.

Referring again to the discussion of Figure 14, as soon as the first 64 (sixty four) bytes of the packet arrive in input FIFO 142, a filtering request is sent to FFP 141. FFP 141 is an extensive filtering mechanism which enables SOC 10 to set inclusive and exclusive filters on any field of a packet from layer 2 to layer 7 of the OSI seven layer model. Filters are used for packet classification based upon a protocol fields in the packets. Various actions are taken based upon the packet classification, including packet discard, sending of the packet to the CPU, sending of the packet to other ports, sending the packet on certain COS priority queues, changing the type of service (TOS) precedence. The exclusive filter is primarily used for implementing security features, and allows a packet to proceed only if there is a filter match. If there is no match, the packet is discarded.

It should be noted that SOC 10 has a unique capability to handle both tagged and untagged packets coming in. Tagged packets are tagged in accordance with IEEE standards, and include a specific IEEE 802.1p priority field for the packet. Untagged packets, however, do not include an 802.1p priority field therein. SOC 10 can assign an appropriate COS value for the packet, which can be considered to be equivalent to a weighted priority, based either upon the destination address or the source address of the packet, as matched in one of the table lookups. As noted in the ARL table format discussed herein, an SCP (Source COS Priority) bit is contained as one of the fields of the table. When this SCP bit is set, then SOC 10 will assign weighted priority based upon a source COS value in the ARL table. If the SCP is not set, then SOC 10 will assign a COS for the packet based upon the destination COS field in the ARL table. These COS values are three bit fields in the ARL table, as noted previously in the ARL table field descriptions.

FFP 141 is essentially a state machine driven programmable rules engine. The filters used by the FFP are 64 (sixty-four) bytes wide, and are applied on an incoming packet; any offset can be used, however, a preferred embodiment uses an offset of zero, and therefore operates on the first 64

bytes, or 512 bits, of a packet. The actions taken by the filter are tag insertion, priority mapping, TOS tag insertion, sending of the packet to the CPU, dropping of the packet, forwarding of the packet to an egress port, and sending the packet to a mirrored port. The filters utilized by FFP 141 are

5 defined by rules table 22. Rules table 22 is completely programmable by CPU 52, through CMIC 40. The rules table can be, for example, 256 entries deep, and may be partitioned for inclusive and exclusive filters, with, again as an example, 128 entries for inclusive filters and 128 entries for exclusive filters. A filter database, within FFP 141, includes a number of inclusive mask

10 registers and exclusive mask registers, such that the filters are formed based upon the rules in rules table 22, and the filters therefore essentially form a 64 byte wide mask or bit map which is applied on the incoming packet. If the filter is designated as an exclusive filter, the filter will exclude all packets unless there is a match. In other words, the exclusive filter allows a packet to

15 go through the forwarding process only if there is a filter match. If there is no filter match, the packet is dropped. In an inclusive filter, if there is no match, no action is taken but the packet is not dropped. Action on an exclusive filter requires an exact match of all filter fields. If there is an exact match with an exclusive filter, therefore, action is taken as specified in the action field; the

20 actions which may be taken, are discussed above. If there is no full match or exact of all of the filter fields, but there is a partial match, then the packet is dropped. A partial match is defined as either a match on the ingress field, egress field, or filter select fields. If there is neither a full match nor a partial match with the packet and the exclusive filter, then no action is taken and the

25 packet proceeds through the forwarding process. The FFP configuration, taking action based upon the first 64 bytes of a packet, enhances the handling of real time traffic since packets can be filtered and action can be taken on the fly. Without an FFP according to the invention, the packet would need to be transferred to the CPU for appropriate action to be interpreted and taken.

30 For inclusive filters, if there is a filter match, action is taken, and if there is no filter match, no action is taken; however, packets are not dropped based on a match or no match situation for inclusive filters.

In summary, the FFP includes a filter database with eight sets of inclusive filters and eight sets of exclusive filters, as separate filter masks. As a packet comes into the FFP, the filter masks are applied to the packet; in other words, a logical AND operation is performed with the mask and the packet. If there is a match, the matching entries are applied to rules tables 22, in order to determine which specific actions will be taken. As mentioned previously, the actions include 802.1p tag insertion, 802.1p priority mapping, IP TOS (type-of-service) tag insertion, sending of the packet to the CPU, discarding or dropping of the packet, forwarding the packet to an egress port, and sending the packet to the mirrored port. Since there are a limited number of fields in the rules table, and since particular rules must be applied for various types of packets, the rules table requirements are minimized in the present invention by the present invention setting all incoming packets to be "tagged" packets; all untagged packets, therefore, are subject to 802.1p tag insertion, in order to reduce the number of entries which are necessary in the rules table. This action eliminates the need for entries regarding handling of untagged packets. It should be noted that specific packet types are defined by various IEEE and other networking standards, and will not be defined herein.

As noted previously, exclusive filters are defined in the rules table as filters which exclude packets for which there is no match; excluded packets are dropped. With inclusive filters, however, packets are not dropped in any circumstances. If there is a match, action is taken as discussed above; if there is no match, no action is taken and the packet proceeds through the forwarding process. Referring to Figure 15, FFP 141 is shown to include filter database 1410 containing filter masks therein, communicating with logic circuitry 1411 for determining packet types and applying appropriate filter masks. After the filter mask is applied as noted above, the result of the application is applied to rules table 22, for appropriate lookup and action. It should be noted that the filter masks, rules tables, and logic, while programmable by CPU 52, do not rely upon CPU 52 for the processing and

calculation thereof. After programming, a hardware configuration is provided which enables linespeed filter application and lookup.

Referring once again to Figure 14, after FFP 141 applies appropriate configured filters and results are obtained from the appropriate rules table 22, logic 1411 in FFP 141 determines and takes the appropriate action. The filtering logic can discard the packet, send the packet to the CPU 52, modify the packet header or IP header, and recalculate any IP checksum fields or takes other appropriate action with respect to the headers. The modification occurs at buffer slicer 144, and the packet is placed on C channel 81. The control message and message header information is applied by the FFP 141 and ARL engine 143, and the message header is placed on P channel 82. Dispatch unit 18, also generally discussed with respect to Figure 8, coordinates all dispatches to C channel, P channel and S channel. As noted previously, each EPIC module 20, GPIC module 30, PMMU 70, etc. are individually configured to communicate via the CPS channel. Each module can be independently modified, and as long as the CPS channel interfaces are maintained, internal modifications to any modules such as EPIC 20a should not affect any other modules such as EPIC 20b, or any GPICs 30.

As mentioned previously, FFP 141 is programmed by the user, through CPU 52, based upon the specific functions which are sought to be handled by each FFP 141. Referring to Figure 17, it can be seen that in step 17-1, an FFP programming step is initiated by the user. Once programming has been initiated, the user identifies the protocol fields of the packet which are to be of interest for the filter, in step 17-2. In step 17-3, the packet type and filter conditions are determined, and in step 17-4, a filter mask is constructed based upon the identified packet type, and the desired filter conditions. The filter mask is essentially a bit map which is applied or ANDed with selected fields of the packet. After the filter mask is constructed, it is then determined whether the filter will be an inclusive or exclusive filter, depending upon the problems which are sought to be solved, the packets which are sought to be forwarded, actions sought to be taken, etc. In step 17-6, it is determined whether or not the filter is on the ingress port, and in step 17-7, it is

determined whether or not the filter is on the egress port. If the filter is on the ingress port, an ingress port mask is used in step 17-8. If it is determined that the filter will be on the egress port, then an egress mask is used in step 17-9. Based upon these steps, a rules table entry for rules tables 22 is then  
5 constructed, and the entry or entries are placed into the appropriate rules table (steps 17-10 and 17-11). These steps are taken through the user inputting particular sets of rules and information into CPU 52 by an appropriate input device, and CPU 52 taking the appropriate action with respect to creating the filters, through CMIC 40 and the appropriate ingress  
10 or egress submodules on an appropriate EPIC module 20 or GPIC module 30.

It should also be noted that the block diagram of SOC 10 in Figure 2 illustrates each GPIC 30 having its own ARL/L3 tables 31, rules table 32, and VLAN tables 33, and also each EPIC 20 also having its own ARL/L3 tables  
15 21, rules table 22, and VLAN tables 23. In a preferred embodiment of the invention, however, two separate modules can share a common ARL/L3 table and a common VLAN table. Each module, however, has its own rules table 22. For example, therefore, GPIC 30a may share ARL/L3 table 21a and VLAN table 23a with EPIC 20a. Similarly, GPIC 30b may share ARL table 21b  
20 and VLAN table 23b with EPIC 20b. This sharing of tables reduces the number of gates which are required to implement the invention, and makes for simplified lookup and synchronization as will be discussed below.

#### **Table Synchronization and Aging**

SOC 10 utilizes a unique method of table synchronization and aging,  
25 to ensure that only current and active address information is maintained in the tables. When ARL/L3 tables are updated to include a new source address, a "hit bit" is set within the table of the "owner" or obtaining module to indicate that the address has been accessed. Also, when a new address is learned and placed in the ARL table, an S channel message is placed on S channel  
30 83 as an ARL insert message, instructing all ARL/L3 tables on SOC 10 to learn this new address. The entry in the ARL/L3 tables includes an identification of the port which initially received the packet and learned the

address. Therefore, if EPIC 20a contains the port which initially received the packet and therefore which initially learned the address, EPIC 20a becomes the "owner" of the address. Only EPIC 20a, therefore, can delete this address from the table. The ARL insert message is received by all of the modules, and the address is added into all of the ARL/L3 tables on SOC 10. CMIC 40 will also send the address information to CPU 52. When each module receives and learns the address information, an acknowledge or ACK message is sent back to EPIC 20a; as the owner further ARL insert messages cannot be sent from EPIC 20a until all ACK messages have been received from all of the modules. In a preferred embodiment of the invention, CMIC 40 does not send an ACK message, since CMIC 40 does not include ingress/egress modules thereupon, but only communicates with CPU 52. If multiple SOC 10 are provided in a stacked configuration, all ARL/L3 tables would be synchronized due to the fact that CPS channel 80 would be shared throughout the stacked modules.

Referring to Figure 18, the ARL aging process is discussed. An age timer is provided within each EPIC module 20 and GPIC module 30, at step 18-1, it is determined whether the age timer has expired. If the timer has expired, the aging process begins by examining the first entry in ARL table 21. At step 18-2, it is determined whether or not the port referred to in the ARL entry belongs to the particular module. If the answer is no, the process proceeds to step 18-3, where it is determined whether or not this entry is the last entry in the table. If the answer is yes at step 18-3, the age timer is restarted and the process is completed at step 18-4. If this is not the last entry in the table, then the process is returned to the next ARL entry at step 18-5. If, however, at step 18-2 it is determined that the port does belong to this particular module, then, at step 18-6 it is determined whether or not the hit bit is set, or if this is a static entry. If the hit bit is set, the hit bit is reset at step 18-7, and the method then proceeds to step 18-3. If the hit bit is not set, the ARL entry is deleted at step 18-8, and a delete ARL entry message is sent on the CPS channel to the other modules, including CMIC 40, so that the table can be appropriately synchronized as noted above. This aging process can

be performed on the ARL (layer two) entries, as well as layer three entries, in order to ensure that aged packets are appropriately deleted from the tables by the owners of the entries. As noted previously, the aging process is only performed on entries where the port referred to belongs to the particular module which is performing the aging process. To this end, therefore, the hit bit is only set in the owner module. The hit bit is not set for entries in tables of other modules which receive the ARL insert message. The hit bit is therefore always set to zero in the synchronized non-owner tables.

The purpose of the source and destination searches, and the overall lookups, is to identify the port number within SOC 10 to which the packet should be directed to after it is placed either CBP 50 or GBP 60. Of course, a source lookup failure results in learning of the source from the source MAC address information in the packet; a destination lookup failure, however, since no port would be identified, results in the packet being sent to all ports on SOC 10. As long as the destination VLAN ID is the same as the source VLAN ID, the packet will propagate the VLAN and reach the ultimate destination, at which point an acknowledgement packet will be received, thereby enabling the ARL table to learn the destination port for use on subsequent packets. If the VLAN IDs are different, an L3 lookup and learning process will be performed, as discussed previously. It should be noted that each EPIC and each GPIC contains a FIFO queue to store ARL insert messages, since, although each module can only send one message at a time, if each module sends an insert message, a queue must be provided for appropriate handling of the messages.

#### **Port Movement**

After the ARL/L3 tables have entries in them, the situation sometimes arises where a particular user or station may change location from one port to another port. In order to prevent transmission errors, therefore, SOC 10 includes capabilities of identifying such movement, and updating the table entries appropriately. For example, if station A, located for example on port 1, seeks to communicate with station B, whose entries indicate that user B is located on port 26. If station B is then moved to a different port, for example,

port 15, a destination lookup failure will occur and the packet will be sent to all ports. When the packet is received by station B at port 15, station B will send an acknowledge (ACK) message, which will be received by the ingress of the EPIC/GPIC module containing port 1 thereupon. A source lookup (of the acknowledge message) will yield a match on the source address, but the port information will not match. The EPIC/GPIC which receives the packet from B, therefore, must delete the old entry from the ARL/L3 table, and also send an ARL/L3 delete message onto the S channel so that all tables are synchronized. Then, the new source information, with the correct port, is inserted into the ARL/L3 table, and an ARL/L3 insert message is placed on the S channel, thereby synchronizing the ARL/L3 tables with the new information. The updated ARL insert message cannot be sent until all of the acknowledgement messages are sent regarding the ARL delete message, to ensure proper table synchronization. As stated previously, typical ARL insertion and deletion commands can only be initiated by the owner module. In the case of port movement, however, since port movement may be identified by any module sending a packet to a moved port, the port movement-related deletion and insertion messages can be initiated by any module.

## 20 **Trunking**

During the configuration process wherein a local area network is configured by an administrator with a plurality of switches, etc., numerous ports can be "trunked" to increase bandwidth. For example, if traffic between a first switch SW1 and a second switch SW2 is anticipated as being high, the LAN can be configured such that a plurality of ports, for example ports 1 and 2, can be connected together. In a 100 megabits per second environment, the trunking of two ports effectively provides an increased bandwidth of 200 megabits per second between the two ports. The two ports 1 and 2, are therefore identified as a trunk group, and CPU 52 is used to properly configure the handling of the trunk group. Once a trunk group is identified, it is treated as a plurality of ports acting as one logical port. Figure 19 illustrates a configuration wherein SW1, containing a plurality of ports thereon, has a

trunk group with ports 1 and 2 of SW2, with the trunk group being two communication lines connecting ports 1 and 2 of each of SW1 and SW2. This forms trunk group T. In this example, station A, connected to port 3 of SW1, is seeking to communicate or send a packet to station B, located on port 26 of switch SW2. The packet must travel, therefore, through trunk group T from port 3 of SW1 to port 26 of SW2. It should be noted that the trunk group could include any of a number of ports between the switches. As traffic flow increases between SW1 and SW2, trunk group T could be reconfigured by the administrator to include more ports, thereby effectively increasing bandwidth. In addition to providing increased bandwidth, trunking provides redundancy in the event of a failure of one of the links between the switches. Once the trunk group is created, a user programs SOC 10 through CPU 52 to recognize the appropriate trunk group or trunk groups, with trunk group identification (TGID) information. A trunk group port bit map is prepared for each TGID; and a trunk group table, provided for each module on SOC 10, is used to implement the trunk group, which can also be called a port bundle. A trunk group bit map table is also provided. These two tables are provided on a per module basis, and, like tables 21, 22, and 23, are implemented in silicon as two-dimensional arrays. In one embodiment of SOC 10, six trunk groups can be supported, with each trunk group having up to eight trunk ports thereupon. For communication, however, in order to prevent out-of-ordering of packets or frames, the same port must be used for packet flow. Identification of which port will be used for communication is based upon any of the following: source MAC address, destination MAC address, source IP address, destination IP address, or combinations of source and destination addresses. If source MAC is used, as an example, if station A on port 3 of SW1 is seeking to send a packet to station B on port 26 of SW2, then the last three bits of the source MAC address of station A, which are in the source address field of the packet, are used to generate a trunk port index. The trunk port index, which is then looked up on the trunk group table by the ingress submodule 14 of the particular port on the switch, in order to determine which port of the trunk group will be used for the communication. In other words,

when a packet is sought to be sent from station A to station B, address resolution is conducted as set forth above. If the packet is to be handled through a trunk group, then a T bit will be set in the ARL entry which is matched by the destination address. If the T bit or trunk bit is set, then the destination address is learned from one of the trunk ports. The egress port, therefore, is not learned from the port number obtained in the ARL entry, but is instead learned from the trunk group ID and rules tag (RTAG) which is picked up from the ARL entry, and which can be used to identify the trunk port based upon the trunk port index contained in the trunk group table. The RTAG and TGID which are contained in the ARL entry therefore define which part of the packet is used to generate the trunk port index. For example, if the RTAG value is 1, then the last three bits of the source MAC address are used to identify the trunk port index; using the trunk group table, the trunk port index can then be used to identify the appropriate trunk port for communication. If the RTAG value is 2, then it is the last three bits of the destination MAC address which are used to generate the trunk port index. If the RTAG is 3, then the last three bits of the source MAC address are XORED with the last three bits of the destination MAC address. The result of this operation is used to generate the trunk port index. For IP packets, additional RTAG values are used so that the source IP and destination IP addresses are used for the trunk port index, rather than the MAC addresses.

SOC 10 is configured such that if a trunk port goes down or fails for any reason, notification is sent through CMIC 40 to CPU 52. CPU 52 is then configured to automatically review the trunk group table, and VLAN tables to make sure that the appropriate port bit maps are changed to reflect the fact that a port has gone down and is therefore removed. Similarly, when the trunk port or link is reestablished, the process has to be reversed and a message must be sent to CPU 52 so that the VLAN tables, trunk group tables, etc. can be updated to reflect the presence of the trunk port.

Furthermore, it should be noted that since the trunk group is treated as a single logical link, the trunk group is configured to accept control frames or control packets, also known as BPDUs, only one of the trunk ports. The port

based VLAN table, therefore, must be configured to reject incoming BPDUs of non-specified trunk ports. This rejection can be easily set by the setting of a B bit in the VLAN table. IEEE standard 802.1d defines an algorithm known as the spanning tree algorithm, for avoiding data loops in switches where trunk groups exist. Referring to Figure 19, a logical loop could exist between ports 1 and 2 and switches SW1 and SW2. The spanning algorithm tree defines four separate states, with these states including disabling, blocking, listening, learning, and forwarding. The port based VLAN table is configured to enable CPU 52 to program the ports for a specific ARL state, so that the ARL logic takes the appropriate action on the incoming packets. As noted previously, the B bit in the VLAN table provides the capability to reject BPDUs. The St bit in the ARL table enables the CPU to learn the static entries; as noted in Figure 18, static entries are not aged by the aging process. The hit bit in the ARL table, as mentioned previously, enables the ARL engine 143 to detect whether or not there was a hit on this entry. In other words, SOC 10 utilizes a unique configuration of ARL tables, VLAN tables, modules, etc. in order to provide an efficient silicon based implementation of the spanning tree states.

In certain situations, such as a destination lookup failure (DLF) where a packet is sent to all ports on a VLAN, or a multicast packet, the trunk group bit map table is configured to pickup appropriate port information so that the packet is not sent back to the members of the same source trunk group. This prevents unnecessary traffic on the LAN, and maintains the efficiency at the trunk group.

## **IP/IPX**

Referring again to Figure 14, each EPIC 20 or GPIC 30 can be configured to enable support of both IP and IPX protocol at linespeed. This flexibility is provided without having any negative effect on system performance, and utilizes a table, implemented in silicon, which can be selected for IP protocol, IPX protocol, or a combination of IP protocol and IPX protocol. This capability is provided within logic circuitry 1411, and utilizes an IP longest prefix cache lookup (IP\_LPC), and an IPX longest prefix cache

lookup (IPX\_LPC). During the layer 3 lookup, a number of concurrent searches are performed; an L3 fast lookup, and the IP longest prefix cache lookup, are concurrently performed if the packet is identified by the packet header as an IP packet. If the packet header identifies the packet as an IPX packet, the L3 fast lookup and the IPX longest prefix cache lookup will be concurrently performed. It should be noted that ARL/L3 tables 21/31 include an IP default router table which is utilized for an IP longest prefix cache lookup when the packet is identified as an IP packet, and also includes an IPX default router table which is utilized when the packet header identifies the packet as an IPX packet. Appropriate hexadecimal codes are used to determine the packet types. If the packet is identified as neither an IP packet nor an IPX packet, the packet is directed to CPU 52 via CPS channel 80 and CMIC 40. It should be noted that if the packet is identified as an IPX packet, it could be any one of four types of IPX packets. The four types are Ethernet 802.3, Ethernet 802.2, Ethernet SNAP, and Ethernet II.

The concurrent lookup of L3 and either IP or IPX are important to the performance of SOC 10. In one embodiment of SOC 10, the L3 table would include a portion which has IP address information, and another portion which has IPX information, as the default router tables. These default router tables, as noted previously, are searched depending upon whether the packet is an IP packet or an IPX packet. In order to more clearly illustrate the tables, the L3 table format for an L3 table within ARL/L3 tables 21 is as follows:

**IP or IPX Address** - 32 bits long - IP or IPX Address - is a 32 bit IP or IPX Address. The Destination IP or IPX Address in a packet is used as a key in searching this table.

**Mac Address** - 48 bits long - Mac Address is really the next Hop Mac Address. This Mac address is used as the Destination Mac Address in the forwarded IP Packet.

**Port Number** - 6 bits long - Port Number - is the port number the packet has to go out if the Destination IP Address matches this entry's IP Address.

**L3 Interface Num** - 5 bits long - L3 Interface Num - This L3 Interface Number is used to get the Router Mac Address from the L3 Interface Table.

5 **L3 Hit Bit** - 1 bit long - L3 Hit bit - is used to check if there is hit on this Entry. The hit bit is set when the Source IP Address search matches this entry. The L3 Aging Process ages the entry if this bit is not set.

**Frame Type** - 2 bits long - Frame Type indicates type of IPX Frame (802.2, Ethernet II, SNAP and 802.3) accepted by this IPX Node. Value 00 - Ethernet II Frame. Value 01 - SNAP Frame. Value 02 - 10 **802.2 Frame. Value 03 - 802.3 Frame.**

**Reserved** - 4 bits long - Reserved for future use.

The fields of the default IP router table are as follows:

15 **IP Subnet Address** - 32 bits long - IP Subnet Address - is a 32 bit IP Address of the Subnet.

**Mac Address** - 48 bits long - Mac Address is really the next Hop Mac Address and in this case is the Mac Address of the default Router.

**Port Number** - 6 bits long - Port Number is the port number forwarded packet has to go out.

20 **L3 Interface Num** - 5 bits long - L3 Interface Num is L3 Interface Number.

**IP Subnet Bits** - 5 bits long - IP Subnet Bits is total number of Subnet Bits in the Subnet Mask. These bits are ANDED with Destination IP Address before comparing with Subnet Address.

25 **C Bit** - 1 bit long - C Bit - If this bit is set then send the packet to CPU also.

The fields of the default IPX router table within ARL/L3 tables 21 are as follows:

30 **IPX Subnet Address** - 32 bits long - IPX Subnet Address is a 32 bit IPX Address of the Subnet.

**Mac Address** - 48 bits long - Mac Address is really the next Hop Mac Address and in this case is the Mac Address of the default Router.

**Port Number** - 6 bits long - Port Number is the port number forwarded packet has to go out.

**L3 Interface Num** - 5 bits long - L3 Interface Num is L3 Interface Number.

5        **IPX Subnet Bits** - 5 bits long - IPX Subnet Bits is total number of Subnet Bits in the Subnet Mask. These bits are ANDED with Destination IPX Address before comparing with Subnet Address.

**C Bit** - 1 bit long - C Bit - If this bit is set then send the packet to CPU also.

10        If a match is not found in the L3 table for the destination IP address, longest prefix match in the default IP router fails, then the packet is given to the CPU. Similarly, if a match is not found on the L3 table for a destination IPX address, and the longest prefix match in the default IPX router fails, then the packet is given to the CPU. The lookups are done in parallel, but if the  
15        destination IP or IPX address is found in the L3 table, then the results of the default router table lookup are abandoned.

      The longest prefix cache lookup, whether it be for IP or IPX, includes repetitive matching attempts of bits of the IP subnet address. The longest prefix match consists of ANDing the destination IP address with the number  
20        of IP or IPX subnet bits and comparing the result with the IP subnet address. Once a longest prefix match is found, as long as the TTL is not equal to one, then appropriate IP check sums are recalculated, the destination MAC address is replaced with the next hop MAC address, and the source MAC address is replaced with the router MAC address of the interface. The VLAN  
25        ID is obtained from the L3 interface table, and the packet is then sent as either tagged or untagged, as appropriate. If the C bit is set, a copy of the packet is sent to the CPU as may be necessary for learning or other CPU-related functions.

      It should be noted, therefore, that if a packet arrives destined to a MAC  
30        address associated with a level 3 interface for a selected VLAN, the ingress looks for a match at an IP/IPX destination subnet level. If there is no IP/IPX destination subnet match, the packet is forwarded to CPU 52 for appropriate

routing. However, if an IP/IPX match is made, then the MAC address of the next hop and the egress port number is identified and the packet is appropriately forwarded.

5 In other words, the ingress of the EPIC 20 or GPIC 30 is configured with respect to ARL/L3 tables 21 so that when a packet enters ingress submodule 14, the ingress can identify whether or not the packet is an IP packet or an IPX packet. IP packets are directed to an IP/ARL lookup, and IPX configured packets are directed to an IPX/ARL lookup. If an L3 match is found during the L3 lookup, then the longest prefix match lookups are  
10 abandoned.

### **HOL Blocking**

SOC 10 incorporates some unique data flow characteristics, in order maximize efficiency and switching speed. In network communications, a concept known as head-of-line or HOL blocking occurs when a port is  
15 attempting to send a packet to a congested port, and immediately behind that packet is another packet which is intended to be sent to an un-congested port. The congestion at the destination port of the first packet would result in delay of the transfer of the second packet to the un-congested port. Each EPIC 20 and GPIC 30 within SOC 10 includes a unique HOL blocking  
20 mechanism in order to maximize throughput and minimize the negative effects that a single congested port would have on traffic going to un-congested ports. For example, if a port on a GPIC 30, with a data rate of, for example, 1000 megabits per second is attempting to send data to another port 24a on EPIC 20a, port 24a would immediately be congested. Each port on each  
25 GPIC 30 and EPIC 20 is programmed by CPU 52 to have a high watermark and a low watermark per port per class of service (COS), with respect to buffer space within CBP 50. The fact that the head of line blocking mechanism enables per port per COS head of line blocking prevention enables a more efficient data flow than that which is known in the art. When  
30 the output queue for a particular port hits the preprogrammed high watermark within the allocated buffer in CBP 50, PMMU 70 sends, on S channel 83, a COS queue status notification to the appropriate ingress module of the

appropriate GPIC 30 or EPIC 20. When the message is received, the active port register corresponding to the COS indicated in the message is updated. If the port bit for that particular port is set to zero, then the ingress is configured to drop all packets going to that port. Although the dropped packets will have a negative effect on communication to the congested port, the dropping of the packets destined for congested ports enables packets going to un-congested ports to be expeditiously forwarded thereto. When the output queue goes below the preprogrammed low watermark, PMMU 70 sends a COS queue status notification message on the sideband channel with the bit set for the port. When the ingress gets this message, the bit corresponding to the port in the active port register for the module can send the packet to the appropriate output queue. By waiting until the output queue goes below the low watermark before re-activating the port, a hysteresis is built into the system to prevent constant activation and deactivation of the port based upon the forwarding of only one packet, or a small number of packets. It should be noted that every module has an active port register. As an example, each COS per port may have four registers for storing the high watermark and the low watermark; these registers can store data in terms of number of cells on the output queue, or in terms of number of packets on the output queue. In the case of a unicast message, the packet is merely dropped; in the case of multicast or broadcast messages, the message is dropped with respect to congested ports, but forwarded to uncongested ports. PMMU 70 includes all logic required to implement this mechanism to prevent HOL blocking, with respect to budgeting of cells and packets. PMMU 70 includes an HOL blocking marker register to implement the mechanism based upon cells. If the local cell count plus the global cell count for a particular egress port exceeds the HOL blocking marker register value, then PMMU 70 sends the HOL status notification message. PMMU 70 can also implement an early HOL notification, through the use of a bit in the PMMU configuration register which is referred to as a Use Advanced Warning Bit. If this bit is set, the PMMU 70 sends the HOL notification message if the local cell count plus

the global cell count plus 121 is greater than the value in the HOL blocking marker register. 121 is the number of cells in a jumbo frame.

5 With respect to the hysteresis discussed above, it should be noted that PMMU 70 implements both a spatial and a temporal hysteresis. When the local cell count plus global cell count value goes below the value in the HOL  
blocking marker register, then a poaching timer value from a PMMU  
configuration register is used to load into a counter. The counter is  
decremented every 32 clock cycles. When the counter reaches 0, PMMU 70  
10 sends the HOL status message with the new port bit map. The bit  
corresponding to the egress port is reset to 0, to indicate that there is no more  
HOL blocking on the egress port. In order to carry on HOL blocking  
prevention based upon packets, a skid mark value is defined in the PMMU  
configuration register. If the number of transaction queue entries plus the skid  
15 mark value is greater than the maximum transaction queue size per COS,  
then PMMU 70 sends the COS queue status message on the S channel.  
Once the ingress port receives this message, the ingress port will stop  
sending packets for this particular port and COS combination. Depending  
upon the configuration and the packet length received for the egress port,  
20 either the head of line blocking for the cell high watermark or the head of line  
blocking for the packet high watermark may be reached first. This  
configuration, therefore, works to prevent either a small series of very large  
packets or a large series of very small packets from creating HOL blocking  
problems.

25 The low watermark discussed previously with respect to CBP  
admission logic is for the purpose of ensuring that independent of traffic  
conditions, each port will have appropriate buffer space allocated in the CBP  
to prevent port starvation, and ensure that each port will be able to  
communicate with every other port to the extent that the network can support  
such communication.

30 Referring again to PMMU 70 illustrated in Figure 10, CBM 71 is  
configured to maximize availability of address pointers associated with  
incoming packets from a free address pool. CBM 71, as noted previously,

stores the first cell pointer until incoming packet 112 is received and assembled either in CBP 50, or GBP 60. If the purge flag of the corresponding P channel message is set, CBM 71 purges the incoming data packet 112, and therefore makes the address pointers GPID/CPID associated with the incoming packet to be available. When the purge flag is set, therefore, CBM 71 essentially flushes or purges the packet from processing of SOC 10, thereby preventing subsequent communication with the associated egress manager 76 associated with the purged packet. CBM 71 is also configured to communicate with egress managers 76 to delete aged and congested packets. Aged and congested packets are directed to CBM 71 based upon the associated starting address pointer, and the reclaim unit within CBM 71 frees the pointers associated with the packets to be deleted; this is, essentially, accomplished by modifying the free address pool to reflect this change. The memory budget value is updated by decrementing the current value of the associated memory by the number of data cells which are purged.

To summarize, resolved packets are placed on C channel 81 by ingress submodule 14 as discussed with respect to Figure 8. CBM 71 interfaces with the CPS channel, and every time there is a cell/packet addressed to an egress port, CBM 71 assigns cell pointers, and manages the linked list. A plurality of concurrent reassembly engines are provided, with one reassembly engine for each egress manager 76, and tracks the frame status. Once a plurality of cells representing a packet is fully written into CBP 50, CBM 71 sends out CPIDs to the respective egress managers, as discussed above. The CPIDs point to the first cell of the packet in the CBP; packet flow is then controlled by egress managers 76 to transaction MACs 140 once the CPID/GPID assignment is completed by CBM 71. The budget register (not shown) of the respective egress manager 76 is appropriately decremented by the number of cells associated with the egress, after the complete packet is written into the CBP 50. EGM 76 writes the appropriate PIDs into its transaction FIFO. Since there are multiple classes of service (COSs), then the egress manager 76 writes the PIDs into the selected

transaction FIFO corresponding to the selected COS. As will be discussed below with respect to Figure 13, each egress manager 76 has its own scheduler interfacing to the transaction pool or transaction FIFO on one side, and the packet pool or packet FIFO on the other side. The transaction FIFO includes all PIDs, and the packet pool or packet FIFO includes only CPIDs. The packet FIFO interfaces to the transaction FIFO, and initiates transmission based upon requests from the transmission MAC. Once transmission is started, data is read from CBP 50 one cell at a time, based upon transaction FIFO requests.

As noted previously, there is one egress manager for each port of every EPIC 20 and GPIC 30, and is associated with egress sub-module 18. Figure 13 illustrates a block diagram of an egress manager 76 communicating with R channel 77. For each data packet 112 received by an ingress submodule 14 of an EPIC 20 of SOC 10, CBM 71 assigns a Pointer Identification (PID); if the packet 112 is admitted to CBP 50, the CBM 71 assigns a CPID, and if the packet 112 is admitted to GBP 60, the CBM 71 assigns a GPID number. At this time, CBM 71 notifies the corresponding egress manager 76 which will handle the packet 112, and passes the PID to the corresponding egress manager 76 through R channel 77. In the case of a unicast packet, only one egress manager 76 would receive the PID. However, if the incoming packet were a multicast or broadcast packet, each egress manager 76 to which the packet is directed will receive the PID. For this reason, a multicast or broadcast packet needs only to be stored once in the appropriate memory, be it either CBP 50 or GBP 60.

Each egress manager 76 includes an R channel interface unit (RCIF) 131, a transaction FIFO 132, a COS manager 133, a scheduler 134, an accelerated packet flush unit (APF) 135, a memory read unit (MRU) 136, a time stamp check unit (TCU) 137, and an untag unit 138. MRU 136 communicates with CMC 79, which is connected to CBP 50. Scheduler 134 is connected to a packet FIFO 139. RCIF 131 handles all messages between CBM 71 and egress manager 76. When a packet 112 is received and stored in SOC 10, CBM 71 passes the packet information to RCIF 131 of the

associated egress manager 76. The packet information will include an indication of whether or not the packet is stored in CBP 50 or GBP 70, the size of the packet, and the PID. RCIF 131 then passes the received packet information to transaction FIFO 132. Transaction FIFO 132 is a fixed depth  
5 FIFO with eight COS priority queues, and is arranged as a matrix with a number of rows and columns. Each column of transaction FIFO 132 represents a class of service (COS), and the total number of rows equals the number of transactions allowed for any one class of service. COS manager 133 works in conjunction with scheduler 134 in order to provide policy based  
10 quality of service (QOS), based upon ethernet standards. As data packets arrive in one or more of the COS priority queues of transaction FIFO 132, scheduler 134 directs a selected packet pointer from one of the priority queues to the packet FIFO 139. The selection of the packet pointer is based upon a queue scheduling algorithm, which is programmed by a user through  
15 CPU 52, within COS manager 133. An example of a COS issue is video, which requires greater bandwidth than text documents. A data packet 112 of video information may therefore be passed to packet FIFO 139 ahead of a packet associated with a text document. The COS manager 133 would therefore direct scheduler 134 to select the packet pointer associated with the  
20 packet of video data.

The COS manager 133 can also be programmed using a strict priority based scheduling method, or a weighted priority based scheduling method of selecting the next packet pointer in transaction FIFO 132. Utilizing a strict priority based scheduling method, each of the eight COS priority queues are  
25 provided with a priority with respect to each other COS queue. Any packets residing in the highest priority COS queue are extracted from transaction FIFO 132 for transmission. On the other hand, utilizing a weighted priority based scheduling scheme, each COS priority queue is provided with a programmable bandwidth. After assigning the queue priority of each COS  
30 queue, each COS priority queue is given a minimum and a maximum bandwidth. The minimum and maximum bandwidth values are user programmable. Once the higher priority queues achieve their minimum

bandwidth value, COS manager 133 allocates any remaining bandwidth based upon any occurrence of exceeding the maximum bandwidth for any one priority queue. This configuration guarantees that a maximum bandwidth will be achieved by the high priority queues, while the lower priority queues  
5 are provided with a lower bandwidth.

The programmable nature of the COS manager enables the scheduling algorithm to be modified based upon a user's specific needs. For example, COS manager 133 can consider a maximum packet delay value which must be met by a transaction FIFO queue. In other words, COS manager 133 can  
10 require that a packet 112 is not delayed in transmission by the maximum packet delay value; this ensures that the data flow of high speed data such as audio, video, and other real time data is continuously and smoothly transmitted.

If the requested packet is located in CBP 50, the CPID is passed from  
15 transaction FIFO 132 to packet FIFO 139. If the requested packet is located in GBP 60, the scheduler initiates a fetch of the packet from GBP 60 to CBP 50; packet FIFO 139 only utilizes valid CPID information, and does not utilize GPID information. The packet FIFO 139 only communicates with the CBP and not the GBP. When the egress seeks to retrieve a packet, the packet  
20 can only be retrieved from the CBP; for this reason, if the requested packet is located in the GBP 50, the scheduler fetches the packet so that the egress can properly retrieve the packet from the CBP.

APF 135 monitors the status of packet FIFO 139. After packet FIFO 139 is full for a specified time period, APF 135 flushes out the packet FIFO.  
25 The CBM reclaim unit is provided with the packet pointers stored in packet FIFO 139 by APF 135, and the reclaim unit is instructed by APF 135 to release the packet pointers as part of the free address pool. APF 135 also disables the ingress port 21 associated with the egress manager 76.

While packet FIFO 139 receives the packet pointers from scheduler  
30 134, MRU 136 extracts the packet pointers for dispatch to the proper egress port. After MRU 136 receives the packet pointer, it passes the packet pointer information to CMC 79, which retrieves each data cell from CBP 50. MRU

136 passes the first data cell 112a, incorporating cell header information, to TCU 137 and untag unit 138. TCU 137 determines whether the packet has aged by comparing the time stamps stored within data cell 112a and the current time. If the storage time is greater than a programmable discard time, then packet 112 is discarded as an aged packet. Additionally, if there is a pending request to untag the data cell 112a, untag unit 138 will remove the tag header prior to dispatching the packet. Tag headers are defined in IEEE Standard 802.1q.

Egress manager 76, through MRU 136, interfaces with transmission FIFO 140, which is a transmission FIFO for an appropriate media access controller (MAC); media access controllers are known in the ethernet art. MRU 136 prefetches the data packet 112 from the appropriate memory, and sends the packet to transmission FIFO 140, flagging the beginning and the ending of the packet. If necessary, transmission FIFO 140 will pad the packet so that the packet is 64 bytes in length.

As shown in Figure 9, packet 112 is sliced or segmented into a plurality of 64 byte data cells for handling within SOC 10. The segmentation of packets into cells simplifies handling thereof, and improves granularity, as well as making it simpler to adapt SOC 10 to cell-based protocols such as ATM. However, before the cells are transmitted out of SOC 10, they must be reassembled into packet format for proper communication in accordance with the appropriate communication protocol. A cell reassembly engine (not shown) is incorporated within each egress of SOC 10 to reassemble the sliced cells 112a and 112b into an appropriately processed and massaged packet for further communication.

Figure 16 is a block diagram showing some of the elements of CPU interface or CMIC 40. In a preferred embodiment, CMIC 40 provides a 32 bit 66 MHz PCI interface, as well as an I2C interface between SOC 10 and external CPU 52. PCI communication is controlled by PCI core 41, and I2C communication is performed by I2C core 42, through CMIC bus 167. As shown in the figure, many CMIC 40 elements communicate with each other through CMIC bus 167. The PCI interface is typically used for configuration

and programming of SOC 10 elements such as rules tables, filter masks, packet handling, etc., as well as moving data to and from the CPU or other PCI uplink. The PCI interface is suitable for high end systems wherein CPU 52 is a powerful CPU and running a sufficient protocol stack as required to support layer two and layer three switching functions. The I2C interface is suitable for low end systems, where CPU 52 is primarily used for initialization. Low end systems would seldom change the configuration of SOC 10 after the switch is up and running.

CPU 52 is treated by SOC 10 as any other port. Therefore, CMIC 40 must provide necessary port functions much like other port functions defined above. CMIC 40 supports all S channel commands and messages, thereby enabling CPU 52 to access the entire packet memory and register set; this also enables CPU 52 to issue insert and delete entries into ARL/L3 tables, issue initialize CFAP/SFAP commands, read/write memory commands and ACKs, read/write register command and ACKs, etc. Internal to SOC 10, CMIC 40 interfaces to C channel 81, P channel 82, and S channel 83, and is capable of acting as an S channel master as well as S channel slave. To this end, CPU 52 must read or write 32-bit D words. For ARL table insertion and deletion, CMIC 40 supports buffering of four insert/delete messages which can be polled or interrupt driven. ARL messages can also be placed directly into CPU memory through a DMA access using an ARL DMA controller 161. DMA controller 161 can interrupt CPU 52 after transfer of any ARL message, or when all the requested ARL packets have been placed into CPU memory.

Communication between CMIC 40 and C channel 81/P channel 82 is performed through the use of CP-channel buffers 162 for buffering C and P channel messages, and CP bus interface 163. S channel ARL message buffers 164 and S channel bus interface 165 enable communication with S channel 83. As noted previously, PIO (Programmed Input/Output) registers are used, as illustrated by SCH PIO registers 166 and PIO registers 168, to access the S channel, as well as to program other control, status, address, and data registers. PIO registers 168 communicate with CMIC bus 167 through I2C slave interface 42a and I2C master interface 42b. DMA controller

161 enables chaining, in memory, thereby allowing CPU 52 to transfer multiple packets of data without continuous CPU intervention. Each DMA channel can therefore be programmed to perform a read or write DMA operation. Specific descriptor formats may be selected as appropriate to execute a desired DMA function according to application rules. For receiving cells from PMMU 70 for transfer to memory, if appropriate, CMIC 40 acts as an egress port, and follows egress protocol as discussed previously. For transferring cells to PMMU 70, CMIC 40 acts as an ingress port, and follows ingress protocol as discussed previously. CMIC 40 checks for active ports, COS queue availability and other ingress functions, as well as supporting the HOL blocking mechanism discussed above. CMIC 40 supports single and burst PIO operations; however, burst should be limited to S channel buffers and ARL insert/delete message buffers. Referring once again to I2C slave interface 42a, the CMIC 40 is configured to have an I2C slave address so that an external I2C master can access registers of CMIC 40. CMIC 40 can inversely operate as an I2C master, and therefore, access other I2C slaves. It should be noted that CMIC 40 can also support MIIM through MIIM interface 169. MIIM support is defined by IEEE Standard 802.3u, and will not be further discussed herein. Similarly, other operational aspects of CMIC 40 are outside of the scope of this invention.

A unique and advantageous aspect of SOC 10 is the ability of doing concurrent lookups with respect to layer two (ARL), layer three, and filtering. When an incoming packet comes in to an ingress submodule 14 of either an EPIC 20 or a GPIC 30, as discussed previously, the module is capable of concurrently performing an address lookup to determine if the destination address is within a same VLAN as a source address; if the VLAN IDs are the same, layer 2 or ARL lookup should be sufficient to properly switch the packet in a store and forward configuration. If the VLAN IDs are different, then layer three switching must occur based upon appropriate identification of the destination address, and switching to an appropriate port to get to the VLAN of the destination address. Layer three switching, therefore, must be performed in order to cross VLAN boundaries. Once SOC 10 determines that

L3 switching is necessary, SOC 10 identifies the MAC address of a destination router, based upon the L3 lookup. L3 lookup is determined based upon a reading in the beginning portion of the packet of whether or not the L3 bit is set. If the L3 bit is set, then L3 lookup will be necessary in order to  
5 identify appropriate routing instructions. If the lookup is unsuccessful, a request is sent to CPU 52 and CPU 52 takes appropriate steps to identify appropriate routing for the packet. Once the CPU has obtained the appropriate routing information, the information is stored in the L3 lookup table, and for the next packet, the lookup will be successful and the packet  
10 will be switched in the store and forward configuration.

The above-discussed configuration of the invention is, in a preferred embodiment, embodied on a semiconductor substrate, such as silicon, with appropriate semiconductor manufacturing techniques and based upon a circuit layout which would, based upon the embodiments discussed above, be  
15 apparent to those skilled in the art. A person of skill in the art with respect to semiconductor design and manufacturing would be able to implement the various modules, interfaces, and tables, buffers, etc. of the present invention onto a single semiconductor substrate, based upon the architectural description discussed above. It would also be within the scope of the  
20 invention to implement the disclosed elements of the invention in discrete electronic components, thereby taking advantage of the functional aspects of the invention without maximizing the advantages through the use of a single semiconductor substrate. Although the invention has been described based upon these preferred embodiments, it would be apparent to those of skilled  
25 in the art that certain modifications, variations, and alternative constructions would be apparent, while remaining within the spirit and scope of the invention. In order to determine the metes and bounds of the invention, therefore, reference should be made to the appended claims.

**CLAIMS:**

1. A network switch for network communications, said network switch comprising:

a first data port interface, said first data port interface supporting a first plurality of data ports transmitting and receiving data at a first data rate;

a second data port interface, said second data port interface supporting a second plurality of data ports transmitting and receiving data at a second data rate;

a CPU interface, said CPU interface configured to communicate with a CPU;

an internal memory, said internal memory communicating with said first data port interface and said at least one second data port interface;

a memory management unit, said memory management unit including an external memory interface for communicating data from at least one of said first data port interface and said second data port interface and an external memory;

a communication channel, said communication channel for communicating data and messaging information between said first data port interface, said second data port interface, said CPU interface, said internal memory, and said memory management unit,

wherein one data port interface of said first data port interface and said second data port interface includes a head-of-line blocking prevention mechanism, said head-of-line blocking prevention mechanism including determination means for determining when head-of-line blocking is occurring based upon cell based and packet based thresholds.

2. A network switch as recited in claim 1, wherein said head-of-line blocking prevention mechanism further includes a communication means for communicating an occurrence of head-of-line blocking by sending a message to an ingress port of the one data port interface, said communication means sending the message if one threshold of the cell-based thresholds and packet-based thresholds is exceeded, said mechanism also including deactivating means for deactivating a congested port at which the head-of-line

blocking occurs, with respect to packets or cells destined for the congested port.

3. A network switch as recited in claim 1, wherein the packet based thresholds are provided on a per port per class of service basis.

4. A network switch as recited in claim 1, wherein said head-of-line blocking prevention mechanism includes an output queue for each data port of the plurality of data ports, said output queue including a high threshold and a low threshold, and wherein said mechanism is configured to deactivate a corresponding port when the output queue hits the high threshold.

5. A network switch as recited in claim 4, wherein said high threshold and said low threshold of said output queue are based upon cell count.

6. A network switch as recited in claim 4, wherein said high threshold and said low threshold are based upon class of service per port for each packet.

7. A network switch as recited in claim 4, wherein a plurality of high thresholds and a plurality of low thresholds are provided, said high thresholds including cell-based and packet-based high thresholds, and said low thresholds including cell-based and packet-based low thresholds.

8. A network switch as recited in claim 1, wherein said memory management unit includes an internal memory counter and an external memory counter for counting data cells in the internal memory and the external memory.

9. A network switch as recited in claim 4, wherein said mechanism is configured to maintain the port in the deactivated state until a level of the output queue goes below the low threshold.

10. A network switch as recited in claim 4, wherein when said output queue goes above the high threshold, the one of the first and second data ports sends a message on said communication channel to deactivate the port.

11. A network switch as recited in claim 4, further comprising an active port register for maintaining a list of active ports, with the head-of-line locking prevention mechanism activating and deactivating ports by setting and unsetting bits in the active port register.

12. A network switch as recited in claim 1, further comprising a priority assignment unit for assigning a weighted priority value to untagged packets entering one of the first data port interface and the second data port interface.

13. A network switch as recited in claim 4, said network switch further comprising an active port register, said active port register including fields identifying which of the plurality of data ports are active, and which of the plurality of data ports have been deactivated.

14. A network switch as recited in claim 1, wherein said head-of-line blocking prevention mechanism includes an output queue for each data port of the plurality of data ports, said output queue including a first high threshold and a first low threshold, said first high and low thresholds being based upon cell count, and a second high threshold and a second low threshold, said second high and low thresholds corresponding to packets on a per class of service per port basis, said mechanism being configured to deactivate a corresponding port when the output queue hits one of the first and second high thresholds.

15. A network switch as recited in claim 14, wherein said mechanism is configured to maintain the port in the deactivated state until a level of the output queue goes below a corresponding low threshold, said corresponding low threshold being either of the first and second low thresholds which corresponds to the exceeded first or second high thresholds.

16. A method of preventing head-of-line blocking in a network switch, said method comprising:

- setting a first high watermark and a first low watermark in an output queue of a port, said first high watermark and said first low watermark being based on a cell count;

- setting a second high watermark and a second low watermark in the output queue of the port, said second high watermark and said second low watermark being based upon packets;

- sending a status notification message on a communication channel when one of the first and second high watermarks are reached, indicating a congested port;

updating an active port register deactivating the congested port when the status notification message is received; and

dropping all packets destined for the congested port from other source ports when the congested port has been deactivated, thereby enabling packets to other destination ports to be sent by the other source ports.

17. A method as recited in claim 16, said method further comprising:  
determining when the output queue goes below the first or second low watermark corresponding to the one of the first and second high watermarks;  
sending a status notification message on the communication channel indicating the output queue dropping below the corresponding low watermark;  
updating the active port register to reactivate the congested port, thereby enabling a formerly congested port to receive packets from the other source ports.

18. A method as recited in claim 16, wherein setting the second high watermark and the second low watermark in the output queue includes setting a high watermark and a low watermark for each one of a plurality of classes-of-service of packets coming into the network switch, thereby providing a per port per class-of-service head-of-line blocking prevention mechanism for the network switch.





Fig. 1






Fig. 3




Fig. 4a




Fig. 4b

**Protocol Channel Messages**

30	28	26	24	22	20	18	16	14	12	10	8	6	4	2	0
Opc ode	I P	I P X	Rese rved	Nxt cell	Src Dest Port			Cos	J	S	E	Cr c	P	O	Len
30	28	26	24	22	20	18	16	14	12	10	8	6	4	2	0
Reserved			Bc/Mc Portbitmap												
30	28	26	24	22	20	18	16	14	12	10	8	6	4	2	0
U	Res	Untagged Portbitmap / Src Port Number (bit0..5)													
30	28	26	24	22	20	18	16	14	12	10	8	6	4	2	0
CPU Opcodes										TimeStamp					

Fig. 5

**Side Band Channel Messages**

30	28	26	24	22	20	18	16	14	12	10	8	6	4	2	0
Opcode			Dest Port / Destination Dev Id			Src Port			DataLen			E	EC ode	Cos	C
Address															
Data															

Fig. 6




Figure 7  
Prior Art




Fig 8




Fig. 9




Fig. 10

Line 0 →	FC   LC   BC/MC   Cpy_cnt(5b)   Cell_length (7b)   CRC (2b)   NC_header (16b)   Src Count(6)   IPX   IP   Time_Stamp (14b)   O bits(2b)   P   NextCellLen(2b)   CpuOpcode(4b)   Cell_data (0-9B)
Line 1 →	Cell_data (10-27) Bytes
Line 2 →	Cell_data (28-45) Bytes
Line 3 →	Cell_data (46-63) Bytes

Fig. 11




Fig. 12




Fig 13




Fig. 14




FIG. 15



## FFP Programming Flow Chart




Fig. 17




Fig. 18




Fig. 19

## INTERNATIONAL SEARCH REPORT

International application No.

PCT/US99/14821

**A. CLASSIFICATION OF SUBJECT MATTER**

IPC(6) : G01R 31/08; H04L 12/28, 12/66

US CL : 370/229,235,401,463,419

According to International Patent Classification (IPC) or to both national classification and IPC

**B. FIELDS SEARCHED**

Minimum documentation searched (classification system followed by classification symbols)

U.S. : 370/229,230,233,235,236,395,412,418,401,463

Documentation searched other than minimum documentation to the extent that such documents are included in the fields searched

Electronic data base consulted during the international search (name of data base and, where practicable, search terms used)

APS: NETWORK SWITCH, SINGLE CHIP, THRESHOLD, HEAD-OF-LINE BLOCKING, ETC.

**C. DOCUMENTS CONSIDERED TO BE RELEVANT**

Category*	Citation of document, with indication, where appropriate, of the relevant passages	Relevant to claim No.
A,P	US 5,831,980 A (VARMA et al.) 03 November 1998, see entire document.	1, 16
A,P	US 5,918,074 A (WRIGHT et al.) 29 June 1999, see entire document.	1
A,P	US 5,856,975 A (ROSTOKER et al.) 05 January 1999, see entire document.	1
A,P	US 5,856,977 A (YANG et al.) 05 January 1999, see entire document.	1
A,P	US 5,809,021 A (DIAZ et al.) 15 September 1998, see entire document.	1
A,P	US 5,898,687 A (HARRIMAN et al.) 27 April 1999, see entire document.	1, 4, 8, 16

☐ Further documents are listed in the continuation of Box C.
 ☐ See patent family annex.

* Special categories of cited documents:	*T* later document published after the international filing date or priority date and not in conflict with the application but cited to understand the principle or theory underlying the invention
*A* document defining the general state of the art which is not considered to be of particular relevance	*X* document of particular relevance; the claimed invention cannot be considered novel or cannot be considered to involve an inventive step when the document is taken alone
*B* earlier document published on or after the international filing date	*Y* document of particular relevance; the claimed invention cannot be considered to involve an inventive step when the document is combined with one or more other such documents, such combination being obvious to a person skilled in the art
*L* document which may throw doubts on priority claim(s) or which is cited to establish the publication date of another citation or other special reason (as specified)	*A* document member of the same patent family
*O* document referring to an oral disclosure, use, exhibition or other means	
*P* document published prior to the international filing date but later than the priority date claimed	

Date of the actual completion of the international search

17 AUGUST 1999

Date of mailing of the international search report

22 OCT 1999

 Name and mailing address of the ISA/US  
 Commissioner of Patents and Trademarks  
 Box PCT  
 Washington, D.C. 20231

Facsimile No. (703) 305-3230

Authorized officer

HANH NGUYEN

Telephone No. (703) 306-5445

Form PCT/ISA/210 (second sheet)(July 1992)\*